

WESTERMO

SXL Software Release Notes Merlin 4100/4400/4600 Series

Release SXL-25.05.68.000

Hardware Models	Merlin4100; Merlin4400; Merlin4600 Series
Revision	1.00.18
Approval status	Approved
Date	15 June 2026
Brief description	Details the release of system software SXL-25.05.68.000 for Merlin4100, Merlin4400 and Merlin4600 Series

Table of Contents

1	Revision history	4
2	Release statement	4
2.1	Firmware information	4
2.2	Hardware platforms	4
3	Mobile module support	5
3.1	LTE	5
3.2	LTE-450	5
4	Security fixes	6
5	Security vulnerabilities	9
6	New features	10
7	Deprecated features	12
8	Known issues	13
9	Problems resolved	14
9.1	General	14
9.2	Scada	16
9.3	Web UI	17
10	Appendix 1: New features history	20
10.1	Release 25.05.24.000	20
10.2	Release 25.04.63.000	25
10.3	Release 25.04.16.000	27
10.4	Release 25.04.13.000	28
10.5	Release 25.04.08.000	29
10.6	Release 25.03.43.014	33
10.7	Release 25.03.43.009	33
10.8	Release 25.03.43.000	35
10.9	Release 25.03.23.000	35
10.10	Release 25.02.99.000	36
10.11	Release 25.02.80.000	37
10.12	Release 25.02.14.032	39
10.13	Release 25.02.14.027	39
10.14	Release 25.02.14.016	40
10.15	Release 25.02.14.013	40
10.16	Release 25.02.14.002	42
10.17	Release 25.02.14.000	42
11	Appendix 2: Problems resolved history	44
11.1	Release 25.05.24.000	44
11.2	Release 25.04.63.000	49
11.3	Release 25.04.16.000	53
11.4	Release 25.04.13.000	54

11.5	Release 25.04.08.000.....	54
11.6	Release 25.03.43.014.....	58
11.7	Release 25.03.43.009.....	59
11.8	Release 25.03.43.000.....	60
11.9	Release 25.02.23.000.....	61
11.10	Release 25.02.99.000.....	63
11.11	Release 25.02.80.000.....	64
11.12	Release 25.02.14.032.....	67
11.13	Release 25.02.14.027.....	67
11.14	Release 25.02.14.016.....	67
11.15	Release 25.02.14.013.....	67
11.16	Release 25.02.14.002.....	69

1 Revision history

Date	Revision	Description
02 November 2021	1.00.00	Release notes for SXL-25.02.14.000
18 November 2021	1.00.01	Release notes for SXL-25.02.14.002
03 March 2022	1.00.02	Release notes for SXL-25.02.14.013
21 March 2022	1.00.03	Release notes for SXL-25.02.14.016
24 May 2022	1.00.04	Release notes for SXL-25.02.14.027
13 October 2022	1.00.05	Release notes for SXL-25.02.14.032
05 January 2023	1.00.06	Release notes for SXL-25.02.80.000
13 February 2023	1.00.07	Release notes for SXL-25.02.99.000
23 March 2023	1.00.08	Release notes for SXL-25.03.23.000
22 May 2023	1.00.09	Release notes for SXL-25.03.43.000
27 September 2023	1.00.10	Release notes for SXL-25.03.43.009
08 December 2023	1.00.11	Release notes for SXL-25.03.43.014
17 July 2024	1.00.12	Release notes for SXL-25.04.08.000
13 August 2024	1.00.13	Release notes for SXL-25.04.13.000
05 September 2024	1.00.14	Release notes for SXL-25.04.16.000
14 April 2025	1.00.15	Release notes for SXL-25.04.63.000
18 July 2025	1.00.16	Release notes for SXL-25.04.78.000
27 November 2025	1.00.17	Release notes for SXL-25.05.24.000
15 June 2026	1.00.18	Release notes for SXL-25.05.68.000

2 Release statement

SXL-25.05.68.000 has formally passed internal acceptance and regression testing and is available for general release on hardware platforms as stated below.

2.1 Firmware information

Filename	Size (bytes)	Build Date	Checksum (md5)
SXL-25.05.68.000.k01.image	19,849,216	15/06/2026	49b3e5854370b79e2af1cc25f1c0a61f

2.2 Hardware platforms

Hardware model	Details
Merlin4100	EN 61000-6 LTE/LTE-450 wireless router with 4 port Ethernet switch (10/100M) with dual use port for RS232 serial or digital input, TPM and secure boot.
Merlin4400	EN50121-4, EN 61000-6 LTE/LTE-450 wireless router with 4 port Ethernet switch (10/100M), TPM and secure boot. Optional dual serial.

Merlin4600

IEC61850-3, EN50121-4, EN 61000-6 LTE/LTE-450 wireless router with 4 port Ethernet switch (10/100M), TPM and secure boot. Optional dual serial, dual SFP (1GbE), USB host, digital IO.

3 Mobile module support

3.1 LTE

Firmware	Code	Module	Region	Cat	2G	3G	LTE
25.04.63.000	PFP	Sierra Wireless WP7611	US	4	-	2,4,5	2,4,5,12,13,14,25,26,66,71
25.03.43.005	QFT	Sierra Wireless WP7702	Global	M1	850/900/1800/1900	-	1,2,3,4,5,8,12,13,17,18,19,20,26,28
25.02.14.027	PFJ	Sierra Wireless WP7609-G	Australia	4	-	1,8	1,3,5,8,40,41
	QFX	SIM7070E	Global	M1	850/900/1800/1900	-	1,2,3,4,5,8,12,13,14,18,19,20,25,26,27,28,31,66,72,85
25.02.14.000	QFZ	Sierra Wireless WP7607-G	EMEA	4	900/1800	1,8	1,3,7,8,20,28
	PFI	Sierra Wireless WP7608-G	Asia/Pacific	4	900/1800	2,4,5	2,4,5,12,13,14,17,66
	PFL	Sierra Wireless WP7610-G	North America	4	-	1,5,8	1,3,5,7,8,28

3.2 LTE-450

Firmware	Code	Module	Cat	2G	3G	LTE
25.05.68.000	RFY	Quectel EG950A	4	-	1,2,4,5,8	LTE:FDD: 1,2,3,4,5,7,8,20,28,31,66,72,87 LTE-TDD: 28,40,41
25.05.24.000	RFH	Telit Cinterion TX62-W-C	M1	-	-	LTE-FDD: 1,3,8,30,28,31,72
25.04.63.000	PFT	Unitac ML620RU	4	-	-	LTE-FDD: 3,7,20,31 LTE-TDD: 40
25.02.80.000	PFN	Unitac ML620DE	4	-	-	LTE-FDD: 3,7,20,72
25.02.14.027	PFC	Unitac ML620EU	4	-	-	LTE-FDD: 3,7,20,31,72
	PFM	Unitac ML660PC	4	-	-	LTE-FDD: 3,20,87

4 Security fixes

Firmware	Module	Description	Severity	Mantis
25.05.68.000	luci	Change HTTP method from GET to POST for various actions in web UI	Low	8290
		Mask password text in web UI for SCADA applications	Low	9159 9276
	strongswan	Fix vulnerabilities: 30_cert_cache_random_patch (CVE-2021-41991) 31_eap_success_patch (CVE-2021-45079)	Medium	9430 9431
	web	Support cookie security with SameSite=Strict, HttpOnly, Secure	Low	9606
25.05.24.000	dropbear	Support SSH-ed25519 host key	Low	8933
	system	Fix file security permissions	Low	6406
		Force root password change on first log in for routers shipped with default credentials	Low	8743
		Mask sensitive information in audit logs	Low	8365
		Support configurable data at rest encryption	Low	6947
25.04.63.000	jquery	Updated to version 3.7.1	Medium	7914
	luci	Added Security-Policy-Header (CSP) to prevent clickjacking	Low	8087
	net-snmpd	Updated to version 5.9.4 Fixes CVE-2022-44793; CVE-2020-15861; CVE-2020-15862; CVE-2019-20892; CVE-2015-8100; CVE-2018-18065; CVE-2018-18066; CVE-2014-2285	Medium	7306
	openVPN	Updated to version 2.5.11 Fixes CVE-2022-0547	Irritant	6238
	pam_tacplus	Avoid potential freeing of non-address Fixes CVE-2020-27743 and CVE-2016-20014	Medium	8002
25.03.16.000	dnsmasq	Updated to version 2.90 Fixes CVE-2023-28450 and CVE-2022-0934	Medium	7796
	dropbear	Updated to version 2024.85	Medium	7560
	frr	Fix CVE-2024-44070. FRRouting (FRR) does not check the actual remaining stream length before taking the TLV value.	Medium	7858
	password	New HMAC password hashing algorithm which uses the HMAC functionality in the TPM as a means of hashing passwords (IEC62443-4-2)	Low	7155
25.04.13.000	PPP	Updated to version 2.5.0	Low	4179
25.04.08.000	dropbear	Updated to 2022.83	Medium	6403 4976
	System	Delete sensitive information from RAM and generate syslog message after use by luci, uhttpd, PAM, openVPN and strongswan (IEC62443-4-2).	-	7164 7166 7167

	System	Perform image digital signature verification in virtual memory prior to loading to flash when using to Web UI and Activator	Low	6721
	uhttpd	Support TLS v1.3 (IEC62443-4-2)	-	6854
25.03.43.005	console	Automatically log out console sessions after 30 mins if inactivity	Low	6884
25.03.23.000	telnetd	Remove telnetd support	Medium	
	password	Resetting password via web UI now requires input of current password	Low	5261
	SSH	Added grace period after console login failure to disrupt brute force attacks	Medium	5853
25.02.80.000	dnsmasq	Updated to 2.85 (CVE-2021-3448)	-	6041
	gpsd	Updated to 3.23.1	-	
	overlay	Implemented automatic overlay clean up to remove ad hoc modifications	-	5374
	snmpd	Application now runs with dedicated unique user and group id instead of root privileges	-	4695
25.02.14.000	arp-scan	Upgraded to version 1.9.7	-	
	iecd	COTP: fixed possible heap buffer overflow when handling message with invalid (zero) value in length field Fixes CVE-2020-7054	-	5320
	iproute2	Upgrade to version 5.13.0	-	
	uClibc	Upgrade to version 0.9.33.2	-	
Fixes prior to 25.02.14.000	busybox	Bunzip2 integer overflow fix. Fixes CVE-2017-15873	-	3534
		Fix BusyBox auto completion vulnerability. Fixes CVE-2017-16544	-	
		Heap-based buffer overflow in the DHCP client (udhcp) before 1.25.0. Fixes CVE-2016-2148	-	3747
		Integer overflow in the DHCP client (udhcp) before 1.25.0. Fixes CVE-2016-2147	-	3747
		Upgraded to version 1.23.2. Fixes CVE-2011-2716	-	
	chrony			
	dropbear			4964
	iecd			4966
	iosrpd			4968
	openvpn	Applications now run with dedicated unique user and group id instead of root privileges	-	4970
	rtud			4971
	rtud			4973
	strongswan			4974
	tservd			5003
	xl2tpd			

chrony	Disable internet command sockets	-	4995
	Upgraded to v3.5.1	-	
curl	Upgraded to version 7.67.0	-	
dnsmasq	Upgraded to 2.78. Fixes CVE-2017-14491; CVE-2017-14492; CVE-2017-14493; CVE-2017-14494; CVE-2017-14495; CVE-2017-14496; CVE-2017-13704	-	
	Upgraded to v2.84 to fix vulnerabilities in DNS response validation Fixes CVE-2020-2568; CVE-2020-25686	-	5618
dropbear	DSS(DSA) key algorithm removed Disable support for MD5, 96 bit MAC and CBC mode syphers	-	3809
	Upgraded to 2017.75. Fixes CVE-2016-7406	-	2933
firewall	Updated iptable rules to provide UDP flood protection, filter out bad TCP flags and moved flood protection to mangle table for performance benefit.	-	3570
iecd	Support for secure Modbus TCP with introduction of modbus TLS security extension	-	
IPSec	Integrate latest strongswan security patches 10_openssl_ecdsa_signature_patch (CVE-2013-2944) 12_is_asn1_patch (CVE-2013-5018) 13_id_dn_match_patch (CVE-2013-6075) 14_ikev1_fragment_patch (CVE-2013-6076) 15_reject_child_sa_patch (CVE-2014-2338) 16_asn1_unwrap_patch (CVE-2014-2891) 17_modp_custom_patch (CVE-2014-9221) 19_enforce_remote_auth_patch (CVE-2015-4171) 20_eap_mschapv2_state_patch (CVE-2015-8023) 21_gmp_mpz_powm_sec_patch (CVE-2017-9022) 22_asn1_choice_patch (CVE-2017-9023) 23_gmp_mpz_export_patch (CVE-2017-11185) 25_stroke_msg_len_patch (CVE-2018-5388) 26_skeyseed_init_patch (CVE-2018-10811) 27_gmp_pkcs1_verify_patch (CVE-2012-2388; CVE-2017-11185; CVE-2018-16152) 28_gmp_pkcs1_overflow_patch (CVE-2018-16151; CVE-2018-161152)	-	4079
keepalived	Upgraded to 1.2.19	-	4226
libpcap	Upgraded to version 1.9.1	-	
netsnmp	Upgraded net-snmp to 5.7.3 for integer overflow fix and snmp_pdu_parse function. Fixes CVE-2008-4309; CVE-2015-5621	-	3609
OpenNHRP	Upgraded to version 0.14.1	-	

OpenVPN	Upgraded to version 2.4.6. Fixes CVE-2018-5390	-	
quagga	Upgraded to version 1.1.0. Fixes CVE-2013-6051; CVE-2013-2236; CVE-2016-4036; CVE-2006-2224; CVE-2006-2223; CVE-2016-1245; CVE-2008-1160	-	3656
reset	Config1 and config2 are now deleted when the router is reset to factory config using the reset button press	-	4996
serial	ATMEL module firmware upgraded to 1.3.18	-	3475
	ATMEL module firmware upgraded to 1.4.1. Fixes watchdog crash when handling large packets and also support for 192kb speed.	-	4335
syslog	Mobile connection failure message in syslog now contains encrypted password.	-	3493
system	Added support for UCI encryption for 3G interface password	-	3639
	New configurable option to use SHA-512 for password hashing	-	5001
tcpdump	Updated to version 4.9.3	-	
tservd	TLS support for TCP server and TCP client mode	-	
uboot	Fix root access via modifiable boot process priority	-	3496
web	Disable RC4 cipher suite (RC4, Export, NULL and low strength cyphers (<128)) in https application and add option to set the minimum supported TLS version for the https server. Minimum TLS supported now 1.0.	-	3809
	Disabled SSL and exclusively use TLS versions 1.0 and higher	-	3809
	Mitigated remote code execution vulnerability in cmd script.	-	4054
	Only a generic web error message is now sent to browser and a verbose message is logged on server side	-	3877
	Removed ability to disable critical system services via web UI	-	4340
	Removed support for scheduled tasks via web UI	-	4376

5 Security vulnerabilities

Module	Short Description	Severity	Mantis
bgpd	Vulnerabilities affecting current version of bgpd CVE-2016-1245	Low	5808
dropbear	Vulnerability affecting current version of dropbear CVE-2025-47203	Medium	8907
frr	Vulnerability affecting current version of frr CVE-2024-27913	Low	8204

openssl	Vulnerabilities affecting current version of openssl CVE-2022-1292, CVE-2022-2097, CVE-2022-4304, CVE-2022-4450, CVE-2023-0215, CVE-2023-0286, CVE-2023-0464, CVE-2023-0465, CVE-2023-0466, CVE-2023-2650, CVE-2023-3817, CVE-2023-4807, CVE-2023-5678	Medium	7301
strongswan	Vulnerabilities affecting current version of strongswan CVE-2025-62291: 36_eap_mschapv2_failure_request_len_patch CVE-2026-25075: 38_eap_tls_avp_len_patch	Medium	9432 9433

6 New features

BGP			
Multiple route maps	Support multiple rules to a BGP route map using BGP route map name option		9179
	<u>Package</u>	<u>Section</u>	<u>Options</u>
	bgpd	routemap	name
Firewall			
Validation	Firewall validation error information now logged to syslog with rule name		9004
Mobile			
Eagle I425	Support Eagle I425 mobile module (QFV; QFW)		9542
Quectel EG950A	Support Quectel EG950A mobile module		
SMS	Support concatenation of SMS for better formatting of long SMS messages		9444
Password Management			
Password Hint	New option to show password requirements when password change is enforce.		9157
	<u>Package</u>	<u>Section</u>	<u>Options</u>
	system	system	password_change_hint
Password History	Support configuration of password history depth		9398
	<u>Package</u>	<u>Section</u>	<u>Options</u>
	system	system	password_history_depth
Password history check	Password history check now disabled by default.		9444
PPP			
Upstream Rate Limit	New option to rate limit upstream bandwidth on a PPP link.		4179
	<u>Package</u>	<u>Section</u>	<u>Options</u>
	network	interface	upstream_rate
Scada			

Data Point export	Data and command points can now be exported using web UI	9561
DNP3 Groups	Added support for DNP3 Groups 110 and 111	9157
Genisys II protocol support	Support Genisys II protocol slave for I/O polling	9467
		9573
		9618
		9619
		9620
9621		
IEC104 to IEC104	Support IEC104 to IEC104 with transparent forwarding to allow forwarding between SCADA IEC104 to RTU IEC104 without having to configure data points.	9609
IEC60870-5-103 client	Support IEC60870-5-103 Master to DNP3 Slave protocol conversion web: <code>scada->iecd->Master Protocols->Master Protocol</code>	8437
		9090
		9089
		9212
MQTT Broker	Support a minimal implementation of MQTT broker web: <code>scada->mqtt broker</code>	9155
MQTT client ID check	Support Client ID check for user accounts	9283
MQTT remote address filter	Support configuration for checking client source IP address against configured IP address in the user record	9281
MQTT Master	Support MQTT Master protocol conversion web: <code>scada->iecd->Master Protocols->Master Protocol</code>	9156
MQTT parsing	Support parsing out multiple values from MQTTM publish payload	9354
SNMP integer data types	Support SNMP data types - Gauge32, Counter32, TimeTicks and Opaque - for SNMP master protocol conversion	9061
		9075
SNMP TCP Routes	Support TCP Route block to SNMP Master protocol conversion to allow multiple instances	9275
SNMP to DNP3	Support conversion from SNMPC and FILE to DNP3 octet strings	9158
Virtual Points	Support IECD virtual points.	9086
		9088
SNMP		
VA-TRAPS-G02	Added NTP query failed to VA-TRAPS-G02 MIB	7313
System		
Factory Reset	Report factory reset and decommissioning events to system log and all connected consoles	9419
Smart EMS	Support Welotec Smart EMS Management System	8489
		9076
Terminal Server		
Serial to GRE mirroring	Support mirroring serial data to <code>gre-tap</code> transport mode interface	9370

UDS		
AT Command scripts	Support new script type <code>CRSD</code> to execute scripts in response to AT commands web: <code>services->user-defined scripts->execution type 'CRSD script'</code> opt: <code>uds.script.exec_type 'crsd'</code>	8873
Web UI		
Administration	Move password hash algorithm configuration option from <code>system->system</code> to <code>security->administration</code>	9319
	Support configuring password regex via web UI	9178
	Support user password change error feedback	9314
Certificates	Support Certificate Signing Request (CSR) generation	9180
Cookie Security	Cookie security is now improved with SameSite=Strict, HttpOnly, Secure to protect against Cross-Site Scripting (XSS) and Cross-Site Request Forgery (CSRF) attacks	9606
Decommission	Added warning pop up for confirming Reset for Decommissioning press	8677
Dynamic DNS	Support missing <code>Use HTTPS and CA Certificate file or path</code>	9195
	Split web UI dynamic DNS configuration into tabs	6973
Event System	Now split into tabs for more structured configuration	9446
Firewall	Web UI now reports invalid firewall rule configuration changes. Port options are now only visible when TCP/UDP protocol is selected.	9004
Mobile Manager	Allow adding/removing mobile manager sections	9222
Status	Move logs - syslog, interface log, changes, dmesg - onto a status page with multiple tabs	9040

7 Deprecated features

Firmware	Package	Description	Mantis
25.05.68.000	Mobile	Removed support for Mobile Roaming Templates. Now supported using Roaming Manager feature.	6093
	OpenVPN	Removed no longer supported <code>HTTP Proxy Retry</code> and <code>Persist Tun</code> options from web UI	9559
	SCADA	Removed no longer supported legacy applications web UI which are now supported by IECD: <code>COSEM HDLC Bridge</code> ; <code>DNPOSD</code> ; <code>IEC101MON</code> ; <code>IOSRVD</code>	9518
25.05.24.000	SCEP	Deprecated <code>strongswan.scep_cert.blocking</code> option. SCEP client will now trigger a strongswan reload should the cert be in use by strongswan	8377
25.04.78.000	mobile	Removed support for downloading a factory config via a SIM card	8373

	OpenVPN	Removed <code>openvpn_recipies</code> package	8504
	zabbix	Removed Zabbix agent	8469
25.04.63.000	network	Mobile operator lock option <code>opformat</code> deprecated. Operator locking (option <code>operator</code>) now only uses PLMN ID.	8254
	mobile	Mobile roaming templates deprecated in favour of Mobile Roaming Manager feature	
	Web/IECD	Removed serial baud rates below 1200 from web UI configuration pages. These values are available via <code>Modbus #1 Serial Speed</code>	8000
25.04.08.000	mobile	Deprecated PPP mode for Quectel and Sierra Wireless modules	7337 7517
		Deprecated Quectel EC20 mobile module support	7337
	strongswan	<code>strongswan.connection.authby</code> deprecated. Now supported by new options <code>localauth</code> ; <code>localauth2</code> ; <code>remoteauth</code> ; <code>remoteauth2</code>	6294
	X25	Deprecated <code>x25d</code> , <code>x25ipd</code> and <code>x25val</code> packages	7467
25.02.14.013	network	Configuration section <code>va_switch</code> deprecated. Ethernet configuration should be done using option <code>ifname</code> configured with driver port names	
	wireless	<code>wireless.wifi-device.type</code> option deprecated	

8 Known issues

Module	Short Description	Mantis
DHCP Server	DHCP server won't assign an address when client moved from one port to another without restart of <code>dnsmasq</code>	8532
GPS	No GPS support for SIMCOM7070	
IECD	IEC61850 master does not send <code>CreateDataSet</code> command to create dynamic datasets.	8799
	IEC61850 master RCB reference is always set to unbuffered mode (RP)	8798
Mobile	Do not display RSSI in mobile stats for 5G mobile modules	7060
	Intermittent mobile crash detected on hardware using Seirra Wireless WP7607 with Quectel EG25G module	8650
	Merlin4407 sometimes reported connection for NB-IOT when <code>service_order</code> set to LTE using WP7607-4 module	8968
	Merlin4407 takes several attempts to make connection on band 28 using WP7607-4 module	8985
Multiwan	Syslog messages showing incorrect interface and SIM combination in certain scenarios	8623
OSPF	When the remote connection (from a remote OSPF peer) is dropped, OSPF crashes intermittently.	5677
SCEP	Syslog shows a misconfigured DN in SCEP	8485

Strongswan	Unable to establish IPSec connections in a VRF when using transport mode	9350
	Strongswan memory footprint increases slowly with tunnel restart	5866
Syslog	No web UI support for syslog filter rules	3705
System	Audit logs do not contain user ID information	9589
	HTTPS multi factor authentication not enforced	8051
	Misleading diagnostic message 'failed to kill...for device portWAN' generated on network restart or ifup	7817
	SSH MFA not being enforced	8047
TPM	When uhttpd certificate is erased a new one is not automatically generated when the key is stored in the TPM	8284
Web	802.1x supplicant missing options <code>method</code> , <code>client_key</code> and <code>client_key_passwd</code>	9324
	DNP3S data points not displayed on IECD status page	9047
	Firewall does not allow port ranges to be entered in the form <code>start:end</code>	9440
	Firewall rules page sort buttons missing arrows	9517
	GRE keepalive options missing from web UI	8840
	L2TP missing options for configuring MTU	9614
	IEC61850M link loading issue when SCL file is uploaded	8558
	Importing a config via web UI leaves previous artefacts intact	9592
	SCEP certificate status not updated upon deletion	8998
	SCEP certificate status not updated upon deletion	8998
	SCEP client missing option <code>key_path</code>	9415
	SNMP: Unable to configure custom SNMP Group Name	9488
	Unable to configure management users via web UI	5503
	Unable to configure monitor inventory section via the web UI	9644
	Unable to configure <code>strongswan.connection.disable_mobike</code> , <code>strongswan.connection.mobike_send_additional_self</code> or <code>strongswan.connection.disable_natt</code> via web UI	5437
	Unable to load .P12 or .PXF certificate files via the web UI	8519
	Web intermittently failing to load when WeConnect is active	7808
Web login while in factconf overwrites config1	9596	
Web UI incorrectly showing SMS enabled when option not present in config	9655	

9 Problems resolved

9.1 General

Module	Short Description	Mantis
Activator	Fix Activator delivering the same password for a user when not present in <code>/etc/passwd</code> which could result in <code>management_users</code> password being set to <code>'x'</code>	9398

	Fix issue caused by space separated cipher list causing Activator active updates to fail when TLS Ciphers are specified in the HTTP Client configuration	9203
AT Command Service	Fix ATH0 handling	8955
	Fix error on modem start with +++ in command phase followed by AT	8956
	Fix AT Command Interpreter process restart using /etc/init.d/crsd restart	9189
	Fix ATH command parsing in idle state	9608
	Keep DTR always high on main serial to stop DSR dropping momentarily when TCP session closes	9617
Certificates	Fix private key loading in PKI command	9072
Connection Watch	Fix Connection Watch operation on a VTI interface	8877
DHCP Client	Update DHCPv6 address and timers when processing a response	9093
Dynamic DNS	Fix Dynamic DNS correctly detecting the IP address when using Unitac mobile modules	9148
	Fix incorrect permissions preventing Dynamic DNS process (ddns) from starting	8803
Ethernet	Fix issue when using a bridge configuration the router intermittently fails to detect link on one of the physical bridge ports, even though the cable is physically connected.	9358
Event System	Fix NTP event generation	7098
	Fix SMS event system events generation in syslog	7088
Firewall	Use the correct IP family for reflections that could cause firewall rule not to be applied	9524
IPSec	Drop traffic matching policy when IPSec tunnel is down	8479
	Fix blackhole handling for destination %any and web UI default	9485
	Fix conntrack flush on IPSec tunnel up	9304
	When an IPSec secret change is detected on execution of /etc/init.d/strongswan reload, a full strongswan restart is forced	9077
LLDP	Set Chassis ID to serial number	9199
	Run on all interfaces when option interfaces is empty.	9198
Mobile	Ensure recipe module restart is ignored on models with single radio Sierra Wireless modules and add syslog message to indicate that /etc/init.d/usb_startup has no effect.	9103
	Ensure Unitac module is in automatic operator search mode after switching SIM to allow connection to new operator network	9211
	Fix APN passwords being shown in syslog when special characters are used in the username or password for Unitac modules	9282
	Fix authentication issues for Unitac modules when using more than one APN	9508
	Fix crash with Unitac modules when default APN is enabled but no APN specified	9343
	Fix delay in Unitac module carrier search on SIM switch	9496

	Fix Merlin4400 intermittently reporting connection for NB-IOT when connected via LTE	8986
	Fix reporting of signal values for Quectel EG950 (RFY) mobile module	9534
	Fix status pattern and add 60 second post download delay for flash write execution when performing Verizon LWM2M FOTA upgrade	8927
	Improvements to Unitac module upgrade from ML620EUV13_RELEASE_2024020 to ML620EUV14_RELEASE_20250627 firmware to fix issue with no data connection after upgrade until reboot	8814
	Start interfaces in ascending context order	9128
Monitor	Removed <code>mcc/mnc</code> code to Monitor in place of obsoleted <code>operator</code> field	9337
Network	Improve static route handling when interface configuration changes	8062
OSPF	Increase the maximum number of <code>igmp_max_memberships</code> from 20 to 128 to fix issues with OSPF configurations with greater than 20 peers	9228
SCEP	Fix SCEP certificate status not updated upon deletion of TPM keys	9050
Syslog	Change log level for <code>jffs2</code> summary warning from notice to debug	9132
	Fix DNS request log entries filling system log	6625
	Fix syslog remote filter issue including hostname in matches	9215
	Remove <code>sensitive data</code> overwritten syslog messages	9315
System	Allow password history depth of zero	9388
	Fix ERROR messages in logs when switching Ethernet ports on Merlin3400 series	9186
	Fix management users <code>max_passwd_age</code> option forcing a password change on every log in	9299
	Fix password hint showing correctly for SSH login	9321
	Fix switching between configurations with and without management users which could result in the user passwords being corrupted.	9398

9.2 Scada

Module	Short Description	Mantis
IECD	Fix <code>iec show point</code> output showing syntax error	7212
DNP3	Allow configuration of DNP3S static and event variations per point and show correct variations per group	9254
	Ensure DNP3 to MQTTS points are sent only on value or quality change	9267
	Fix analog output event processing for DNP3S Group 40/41/42	9255
	Fix DNP3 client startup with support for unsolicited mode	9192
	Fix IEC101 to DNP3 unsolicited messages	9272
	Fix incorrect and missing cases of DNP3S Double 64 bit, analog input and analog output support	9252
	Fix incorrect conversion of DNP3-M G3/G4 to Modbus-S DI/CO	9262
	Fix incorrect conversion of floating point objects from DNP3M to MQTTS	8181
	Fix issues processing MQTTS to DNP3M binary and analog output commands	9265

IEC101	Added missing support for TI 21 in IEC104 to IEC101 protocol conversion	9379
	Fix issues with points online offline reporting for IEC101M to Modbus-S scenario	9384
	Fix IV bit handling during IEC101M GI	9381
IEC103	Fixed format spec of <code>iec103m_gi_time_secs</code> in config table	9102
IEC104	Fix incorrect reporting of integrated totals in response to counter interrogation command	9383
	Fix message loss bug when using background scan procedure	9380
	Support regulating step commands (Type ID47 and ID64) for IEC104 to IEC104 protocol conversion	8193
Modbus	Fix incorrect conversion of IEC104 double point to Modbus HR	8159
	Fixed incorrect online-offline reporting of Multi RTU Modbus points	9057
	Modbus TCP - invalidate only points belonging to specific slave address rather than all points	9073
MQTT	Add support for Client ID check to user accounts	9283
	Added configuration and checking for client source IP address against configured IP address in the user record	9281
	Added missing handling of QoS=1 publish messages	9347
	Fix incorrect handling of MQTT to Modbus 32-64 bit float writes	9388
	Fix issues with MQTT initialisation script <code>/etc/init.d/mqttd start</code>	9280
	Fix crash caused by processing SNMP command result	5724
RTUD	Added missing handling of online-offline status bit when reporting GPIO to DNP3	9038
	Improvements to auto config feature	9546 9564

9.3 Web UI

Module	Short Description	Mantis
UI	Change HTTP method from GET to POST for delete actions of SCEP client; IPsec and system clock setting; NTP timeserver enable action; state-changing CBI parse actions in Interfaces and WiFi; Service restart action	8290
	Do not display serial options if serial interface not present on hardware	8414
	Ensure the web UI does not create different config sections with the same name	9081
	Fix user log in when password contains =	9309
	Fix Web UI CSS caching to improve web UI performance	9064
	Improvements to performance of web UI when waiting for a response from a web client that has closed the connection	9037
	Only show applications requiring serial interfaces when serial interfaces are present	8419
	Remove VA references from autoloader, monitor and COSEMD pages	9503

Administration	Fix log in banner description	9187
	Log in banner configuration change now takes effect after Save&Apply instead of reboot.	9191
AT Command Service	Fix broken link on Custom AT commands button web: services->AT command service->advanced	9068
	Fix Serial Failover description in Main Settings	9287
	Support missing options <code>pre_dial_timeout_ms</code> and <code>pre_dial_age_timeout_ms</code>	9205
	Use POST for adding CRSD route and command sections	8290
BGP	Ensure that the routing section for BGP is named <code>bgpd</code>	8078
Certificates	Replace VA references with 'System' for certificates page	9434
Data Usage	Fix web UI crashes when missing configuration options	8915
Diagnostics	Use POST for diagnostic commands such as <code>ping</code> , <code>tracert</code> , and <code>nslookup</code>	8290
Ethernet	Fix Ethernet port counters on web UI	9074
Event System	Remove VA reference from option labels and descriptions	9437
Firewall	Convert firewall restart and reset counter actions to POST	8290
	Fix 404 Not Found error when adding protocol <code>Other</code> on the Port Forwards page	9196
	Only display firewall rule Source/Destination Port fields when TCP/UDP protocol	9004
Interfaces	Support missing <code>gretap</code> , <code>gre6</code> and <code>gretap6</code> interface protocol configuration	9101
	Convert network shutdown, start, delete and add actions to POST	8290
IPSec	Only show aggressive mode option when IKEv1 selected	9130
	Remove 30 character limit from strongswan PSK secret and selector fields when configuring via web UI	9107
Logs	Use POST for clearing interface logs	8290
Mobile	Do not display SMS options when SMS not supported by the radio module	9446
	Do not show SMS options if module does not support SMS	9342
	Fix SIM2 configuration on web UI for SIM7070E mobile module	9605
	Remove 5G references for radio protocol and replace with 'Cellular'	8080
Roaming Manager	Support missing <code>roaming_service</code> option values <code>[cdma 5g any]</code>	9049
RTUD	Only display configuration options for RTU protocol selected	9544
Scada	Added Packed Single Point message type web UI configuration for IEC104 and IEC101 protocol conversions	9380
	Fix Command Point TypeID dropdown menu missing TI 47 (Server 104) for IEC101S	9377
	Fix description on RTUD main page	9274
	Fix issue with web UI points not showing in IECD Status for Modbus-S to DNP3-M scenario	9261
	Fix issues with MQTT TLS certificate file uploads	9278

	Fix MQTT master points not showing in the IECD status	9349
	IECD description now updated to include new protocol conversions	9359
	IECD status page now correctly displays GROUPS 110 and 111	9345
	Improved reporting of points online-offline status (DNP3-M to MQTTs)	9266
	Improvements to IECD showing points on status page	9213
	Move IEC104 options from general configuration tab to IEC104 tab	9580
	Only show RTUD configuration when digital IO's are present	9519
	Support missing TI-5 data point configuration for IEC101 to IEC104 protocol conversion	9376
	Support RTUD configuration on platforms with Digital IO's	9248
SCEP	Only display valid users for SCEP client Certificate User option	9422
	Fix typo in description for Renewal and Retry options	9414
Smart EMS	Use POST for Smart EMS check	8290
SNMP	Fix SNMP web UI configuration when options not already present in configuration	9390
	Remove unsupported 'any' value from SNMP Group Version option list	9601
Status	Only show Data Usage status when data usage enabled	8915
	Only show VRRP status when enabled	6966
Terminal Server	Fix terminal server not showing for firmware families that do not support SCADA	9289
VRRP	Add IP address validation and update description for Virtual IP option	3852

10 Appendix 1: New features history

10.1 Release 25.05.24.000

802.1x				
Port based 802.1x	New option to specify bridge ports where 802.1x is only required on selected ports			8234
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	ieee8021x	authenticator	ports	
Cwatch				
Jitter and latency detection	Support new options to specify maximum permitted jitter and latency			8095
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	cwatch	watch	icmp_jitter_check_enabled; icmp_max_jitter; icmp_latency_check_enabled; icmp_max_latency; icmp_max_average_latency	
Ping interval configuration	Support configuration of cwatch ping interval. Previously hardcoded to 10 seconds.			7350
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	cwatch	watch	icmp_interval	
Dropbear				
Ed25519 support	Support SSH-ed25519 host key for SSH server authentication			8933
SSH algorithm configuration	Support configuration of cipher, host key and key exchange algorithms for SSH connections			8344
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	dropbear	dropbear	cipher; sign_algo; kex_algo	
Event System				
Multiwan events	Added multiwan class and events for group start, interface acquisition and interface state changes to the Event System			8807
	<u>Class</u>	<u>Id</u>	<u>Name</u>	<u>Severity</u>
	multiwan	1	MultiwanGroupStart	informat
				<u>Event Template</u>
				Multiwan group %p1 started with %p2 interfaces
	multiwan	2	MultiwanInterfaceAcquired	informat
				Multiwan group %p1: interface %p2 initial state is %p3
	multiwan	3	MultiwanInterfaceStateChange	informat
				Multiwan group %p1: interface %p2 was %p3 now %p4
HTTP Client				
SSL cipher configuration	Added support for configuration of supported SSL ciphers			8367
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	httpclient	core	TLS13Cipher; LegacyCiphers	

HTTP Server				
TLS cipher configuration	Added support for limiting allowed TLS ciphers			7121
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	uhttpd	uhttpd	tls_ciphers	
Mobile				
LWM2M FOTA support	Support Verizon LWM2M FOTA upgrade			8927
Telit Cinterion support	Support Telit Cinterion TX62-W-C LTE-M mobile module			8988
Multiwan				
Jitter and latency detection	Support new options to specify maximum permitted jitter and latency for a multiwan interface			8435
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	multiwan	interface	icmp_jitter_check_enabled; icmp_max_jitter; icmp_latency_check_enabled; icmp_max_latency; icmp_max_average_latency	
Network				
Link Layer Discovery Protocol	Added support for LLDP functionality.			8505
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	lldp	lldp	enabled; readonly_mode; interfaces; mgmt_ip; description	
NTP				
Time sync on boot only	Support time sync on boot only for scenario where SCADA time source is used but NTP required to sync on boot			8929
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	system	timeserver	initial_sync_only_enabled	
Password Management				
ERE regex support	Support Extended Regular Expressions (ERE) for password regex rules			8905
Force password change on expiration	Support password change on expiration so that when a management user is logging in with an expired password, they are immediately prompted to change the password			8770
Force password change on first log in	Routers shipped with the default root password now require the root password is changed on first log in using a password policy of >= 16 chars. This is required on first connection attempt via console, SSH or web UI.			8743
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	managemen t_user	user	change_password_on_first_login	
Root password lifetime	Extend password lifetime support to cover root management users			8749
OpenVPN				

Two factor authentication	Added support for 2FA for OpenVPN using PAM module. New server-side authentication of client provided username and password against local PAM.			8098
	<u>Package</u>	<u>Section</u>	<u>Options</u>	8543
	openvpn	openvpn	pamauth_enabled	
	system	pam_auth	pamservice 'openvpn'	
Scada				
DNP3 class assignment	Support for class assignment to DNP3 data points on server side.			8889
DNP3 Deadband	Support deadband functionality to DNP3S points.			8890
Health Point multiple RTU tracking	Added support for health point list to track data link state of multiple RTUs			8687
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	iecd	point	iec104_track_rtu_hp_ioa	
IEC104S ActTerm	Added ability to skip waiting for ACTTERM message as some clients and servers do not support it			8624
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	iecd	port	iec104_no_tx_act_term; iec104m_nowait_act_term	
IEC61850 extended RTU support	Added support for up to 30 local RTUs for IEC104 to IEC61850 protocol conversion			8353 8570
MQTT upload certs	Support upload of certificates for MQTT Server			
MQTT SNI extension	Support for Server Name Indication (SNI) extension. SNI is part of TLS client hello and contains a copy of server hostname - required by some MQTT brokers to authenticate the connecting client			8851
SNMP Master Protocol	Support SNMP protocol as a new master RTU protocol			8928
SCEP				
Cisco CA Type	Support CA Type 'cisco' in SCEP Client			8464
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	strongswan	scep_cert	caimpl 'cisco'	
SNMP				
VA-MULIT-IO MIB	SNMP support for digital IO's using VA-MULTI-IO MIB			6478
Strongswan				
XAUTH-PAM authentication	Support xauth-pam authentication. A responder-side authentication variant for ikev1 where credentials are accepted via XAuth and checked against PAM			8420
	<u>Package</u>	<u>Section</u>	<u>Options</u>	8543
	strongswan	connection	remoteauth 'xauth-pam'; remoteauth2 'xauth-pam'	
	system	pam_auth	pamservice 'ipsec'	

System			
CPU temperature	Added support to show CPU temperature cli: showtemp		6478
Factory Reset	New factory reset from command line with customised reset behaviour control cli: va_factory_reset.sh		8974
Overlay Encryption	Added support for data at rest encryption		6947
	Package	Section	
	system	failsafe	encrypt_overlay
TPM			
ECC key generation	Added support for generation of ECC keys in TPM		8415
Web UI			
Authentication	PAM configuration moved to Security section web: Security->Authentication		8787
Certificate Management	New web UI page added for management of certificates and keys web: security->certificates		8464
Connection Watch	Individual tabs for each connection watch configuration and new cwatch status page added to web UI web: Status->Connection Watch		6973
Customised factory reset	Added Factory Reset, Factory Reset and Certificate Deletion and Reset for Decommissioning operations web: System->Flash Operations		8403
Event System	Add Ethernet LinkUp/LinkDown events to event filters list		8792
GNSS	Automatically refresh GPS satellite information every 5 seconds		8537
	Add sky view for GNSS satellites		8537
HTTP Server	Support disabling web UI option in web UI web: Security->HTTP Server->Enable this web UI cli: uhttpd.main.webui_enabled		8730
Inventory	Support SNMP inventory configuration web: system->snmp->Inventory web: system->snmp->IF Table		9000
IPSec	Add IPSec status to Status Overview when IPSec is enabled		6965
Log in	Support force password change via web UI		8743
Mobile Roaming Manager	Support Mobile Roaming Manager network configuration via web UI web: network->interfaces->mobile interface->Roaming Manager		6976
Multiwan	Individual tabs for each Multiwan interface. Configured interfaces now presented as selection rather than text		8435

	<p>Support Mobile Roaming Manager multiwan configuration via web UI</p> <p>web: network->multiwan->wan interfaces->general->Interface Scanning Timeout</p> <p>opt: multiwan.interface.ifup_scanning_timeout_sec</p> <p>web: network->multiwan->wan interfaces->general->Retry on first fail</p> <p>opt: multiwan.interface.retry_on_first_fail</p> <p>web: network->multiwan->wan interfaces->general->Connection Retry Timeout</p> <p>opt: multiwan.interface.retry_connection_max_sec</p>	6976
OpenVPN	<p>Support push routes for OpenVPN server mode</p> <p>web: VPN->OpenVPN->Advanced->Push</p> <p>cli: list push 'route <ip> <mask>'</p>	8712
PPPoE interface	<p>Support configuration of multiple PPPoE interfaces on the same Ethernet link</p>	4287
SCADA	<p>Added display of statistic counters to IECD status page</p> <p>cli: iec show stats</p>	8338
	<p>Enhancements to DNP3S point group ID selector configuration</p>	8514
	<p>IECD Slave configuration changed to IECD Server</p>	8894
	<p>Move MQTT Topic configuration options into a separate tab</p>	8685
	<p>Move VHMI configuration into a separate tab</p>	8530
	<p>Support upload of certificates for MQTT server</p> <p>web: scada->iecd->server protocol->configured mqtt->TLS</p>	8951
SCEP	<p>Enhancements to SCEP Client configuration</p> <ul style="list-style-type: none"> • moved SCEP Client configuration to Certificate Management page • add check for PSK length • added SCEP Client status 	8464
SSH	<p>Removed <code>kex-strict-s-v00@openssh.com</code> from the web UI list of configurable SSH key exchange algorithms. It is now always added to the allowed key exchange algorithm list.</p>	8917
STP Status	<p>Added Spanning Tree Protocol status of bridge interfaces</p> <p>web: status->stp status</p>	8791
System	<p>Support masking of passwords in configuration audit logs</p> <p>web: system->audit configuration->Mask Passwords</p> <p>cli: system.system.audit_cfg_mask_passwords</p>	8365
Time Synchronisation	<p>Support NTP time sync on boot configuration</p> <p>web: system->time synchronization->Enable Boot-Time Only Time Sync</p>	8929
User-Defined Scripts	<p>Individual tabs for each UDS and new UDS overview page</p>	8361

10.2Release 25.04.63.000

Ethernet						
RSTP support	Added support for Rapid Spanning Tree Protocol				6508	
Event System						
	VA Event System now supports firewall discard event					
Event System firewall discard	<u>Class</u>	<u>Id</u>	<u>Name</u>	<u>Severity</u>	<u>Event Template</u>	7769
	Firewal l	2	DiscardZon e	warning	Rule %{p1} triggered: %{p6} from %{p4}:%{p7}(%{p2}) to %{p5}:%{p8}(%{p3})	
Firewall						
Firewall discard event forwarding	New option to support raising an event for rejected/dropped traffic in a firewall zone for onward forwarding to an event system target (snmp, syslog, etc) The packet/event rate will be limited to 10/min by default. Use the <code>log_limit</code> option to change the default packet rate limit if required.				7769	
	<u>Package</u>	<u>Section</u>	<u>Options</u>			
	firewall	zone	discard_event			
Mobile						
PRI display	Added PRI to mobile stats for Sierra Wireless modules <code>cli: vam -a</code>				7440	
SIM7070E diagnostic port	Added support for SIMCOM7070E diagnostic port				7979	
Monitor						
EID Inventory	Support for inventory collection of SIM EID information				8030	
Multiwan						
Suppress static routes	New option to suppress all static routes for an interface when it transitions to failed state				7809	
	<u>Package</u>	<u>Section</u>	<u>Options</u>			
	multiwan	interface	suppress_all_routes_on_fail			
Network						
Interface Status	Include physical ports with eth-X interfaces in interface status				7900	
Multi Path Routes	Support wildcards on interface names to show all matches. <code>cli: ifstatus eth0</code> (matches only eth0) <code>cli: ifstatus eth*</code> (matches all eth interfaces)				7440	
NTP						

NTP min/max poll interval	Allow configuration of minpoll and maxpoll interval using existing NTP interval hours option (space separated parameters)			8318
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	system	timeserver	interval_hours	
Password Scrambling				
Monitor SNMP v3 passwords	Monitor SNMP v3 password options now added to the set of passwords fields that can be scrambled			8090
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	monitor	keepalive	snmp_auth_pass; snmp_priv_pass	
PPP				
BCP support	Added support for Bridge Control Protocol for bridging Ethernet packets through a PPP link. Supported for PPP and L2TP protocols.			7935
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	network	interface	bc; maclcal	
Routing				
PIM Multicast	PIM multicast support is now available via the FRR module			8362
Scada				
Automatic IEC104 point configuration	Support automatic IEC104 point configuration after IEC61850 SCL file import			8248
DNP3 G10 and G41	Support conversion from DNP3 Binary Output Command G10 and G41 to IEC60870-5-101			8100
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	iecd	point	iec101_qu	
DNP3 Multidrop	DNP3 master now supports communication with two RTU over a single serial link. All existing DNP3 master options now have <u>link2_options</u>			8313
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	iecd	port	dnp3_num_links; dnp3_transport_protocol 'multidrop'; dnp3_link2_transport_protocol 'multidrop'	
IEC101 to IEC104 Fully Transparent mode	Support IEC104 to IEC101 transparent mode which allows any ASDU CA when ca configured in the link is zero. Also provides ability to replace IEC101 message TypeID with another configured TypeID before it is transmitted to IEC104.			8161
IEC104 Type ID 51 and 64	Support for IEC104 Slave to IEC104 Master Bitstring command conversion			8192
Modbus TCP	Added TCP port number to route config			7977
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	iecd	port	modbus_tcp_server_port	

Optional DNP3 G40 status	Support optional reporting of DNP3 G40 analog output during integrity poll			7999
	Package	Section	Options	
	iecd	port	dnp3s_g40_exclude_intpoll	
VRTU data types	Support VRTU data types and periodic auto updating per point			8233
	Package	Section	Options	
	iecd	point	vrtu_value_type; vrtu_value_init; vrtu_periodic_value_change	
SNMP				
EID OID	SIM EID now supported in VA-MODEM-MIB			8029
VA-UCI-MIB alias ifNumber	Defines the Alias ifNumber for the uciIfTable (VA-UCI-MIB) for ensuring interfaces in the uciIfTable persistent across reboots and configuration changes.			8094
	Package	Section	Options	
	network	interface	uci_alias_ifnumber	
Strongswan				
VRF support	New option to bind an IPsec tunnel to a VRF. Note: this is only supported for IPv4 ESP tunnel mode.			4307
	Package	Section	Options	
	strongswan	general	vrf	
System				
Firmware and configuration rollback	Support automatic rollback of firmware or configuration if router fails to reconnect to Activator after firmware or configuration update using Activation or Active Update. Feature enabled by default.			3012
	Package	Section	Options	
	rollback	core	enabled; timer	
Merlin4600 Sierra Wireless with 6 Ethernet	Added support for Merlin4600 using single Sierra Wireless mobile with 6 Ethernet (machtype: MTSWI015)			8242
Multi factor Authentication	New authentication method added to PAM Authentication for MFA configuration to persist through reboot.			7152
	Package	Section	Options	
	system	pam_auth	type 'google'	
Unified debug script	Support debug tool which gives a consistent and user-friendly method of enabling debug on various applications. Currently supported for Mobile, IPsec and Multiwan			4677
	cli: debug mobile on cli: debug ipsec on cli: debug multiwan on			

10.3Release 25.04.16.000

Mobile

LTE power saving mode	Support LTE PSM mode for SIMCom7070E mobile module			7841
	Package	Section	Options	
	mobile	mobile	sim1_enable_psm; sim2_enable_psm	
System				
Merlin4405 support	Support for Merlin4405 variant without serial interfaces			
TPM hashed password	Support new HMAC hashing algorithm for hardware with a TPM. This allows the user to use the HMAC functionality in the TPM as a means of hashing passwords. This is opposed to existing md5 or sha512 hashes and prevents a malicious actor from decrypting as the hashes now require the TPM hardware to be calculated			7155
	Package	Section	Options	
	system	system	password_hash_algo 'hmac'	

10.4Release 25.04.13.000

Console				
Console disable	Support new option for disabling the console port			7802
	Package	Section	Options	
	system	failsafe	console	
Mobile				
SKU display	Add display of Sierra Wireless module SKU to mobile diagnostics			7155
PPP				
Adaptive LCP Echo	When enabled LCP echo will only be sent if no traffic is received on the interface. This avoids the situation where PPP is terminated on a congested PPP link because LCP echos are not received in time (Mantis: 4179)			4179
	Package	Section	Options	
	network	interface	adaptive_keepalive	
System				
Change Log	Change log now records active image number and version on reboot			7728
Merlin4400 series without serial	Added support for Merlin4400 series with no serial interface			7722
Merlin4600 dual mobile	Added support for Merlin4600 series with dual mobile			7714
Merlin4700 with SFP	Added support for Merlin4700 with additional SFP/Ethernet port			7717
Port mirroring	Support software port mirroring. All ingress and egress traffic on an interface can be mirrored to an alternate interface			7969
	Package	Section	Options	
	network	interface	mirrorto	

Change Log	Change log now records active image number and version on reboot	7728
Merlin4400 series without serial	Added support for Merlin4400 series with no serial interface	7722

10.5Release 25.04.08.000

AT Command Service														
AT Command Service	New router application that acts as a PSTN modem emulator/AT command interpreter. It converts PSTN data calls from asynchronous serial to TCP/IP.													
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>crsd</td> <td>main</td> <td>see user manual</td> </tr> <tr> <td></td> <td>route</td> <td></td> </tr> <tr> <td></td> <td>translate</td> <td></td> </tr> </tbody> </table>	Package	Section	Options	crsd	main	see user manual		route			translate		
Package	Section	Options												
crsd	main	see user manual												
	route													
	translate													
Dual user serial/digital input port														
Merlin4400 support	Merlin4400 series now supports a dual use serial/digital input port	7214												
Management Users														
User groups	Support new group configuration which contains a list of <code>allowed_pages</code> . A user can be assigned to multiple groups. This allows a user to be able to visit pages from their own <code>allowed_pages</code> as well as from any assigned groups	7158												
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>management_user</td> <td>user_group</td> <td>groups</td> </tr> <tr> <td></td> <td></td> <td>enabled; allowed_pages</td> </tr> </tbody> </table>	Package	Section	Options	management_user	user_group	groups			enabled; allowed_pages				
Package	Section	Options												
management_user	user_group	groups												
		enabled; allowed_pages												
Mobile														
Airplane mode in backoff	Support new option to enter Airplane Mode during the interface back off period	7032												
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>network</td> <td>interface</td> <td>airplane_mode_backoff</td> </tr> </tbody> </table>	Package	Section	Options	network	interface	airplane_mode_backoff							
Package	Section	Options												
network	interface	airplane_mode_backoff												
SMS security	Improvements to SMS queue processing and support new options for better control how SMS messages are handled	3976												
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>mobile</td> <td>mobile</td> <td>sms_read_interval; sms_check_time; sms_past_margin; sms_future_margin</td> </tr> </tbody> </table>	Package	Section	Options	mobile	mobile	sms_read_interval; sms_check_time; sms_past_margin; sms_future_margin							
Package	Section	Options												
mobile	mobile	sms_read_interval; sms_check_time; sms_past_margin; sms_future_margin												
SMS whitelisting	Support whitelisting commands allowed to be executable by SMS	6931												
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>mobile</td> <td>caller</td> <td>allowed_commands</td> </tr> </tbody> </table>	Package	Section	Options	mobile	caller	allowed_commands							
Package	Section	Options												
mobile	caller	allowed_commands												

Watchdog timeout behaviour	Support advanced configurable action [<code>log reset reboot</code>] to take when a watchdog timeout occurs for a mobile module. Currently only supported for QMI modules			5719
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	mobile	main	netdev_wd_action	
OpenVPN				
TPM support	Support OpenVPN keys in TPM. The existing key option should be configured to the TPM label for the OpenVPN key			7126
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	openvpn	openvpn	keytype; key '<TPM-label>'	
Password Management				
Multi Factor Authentication	SSH and web UI now support Multi Factor Authentication using Google authenticator			5339
	<u>Package</u>	<u>Section</u>	<u>Options</u>	7152
	dropbear	dropbear	multi_factor_auth	7154
	luci	main	multi_factor_auth	
Password lifetime	Support password lifetime configuration for management users. Does not apply to root password			7156
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	managemen t_user	user	max_passwd_age	
Password regex	Support configuring password regex rules. Applies to root password and management users password			7194
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	system	main	password_regex	
Password reuse	Support limiting password re-use of the last 10 management user passwords. Does not apply to root password			
RADIUS				
NAS-Identifier option	Support new configuration option for NAS-Identifier with support for <code>%serial</code> and <code>%hostname</code> option values			7347
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	system	pam_auth	radius_nasid	
Scada				
AI Scaler	Extended AI scaler support <code>iecd.port.ai_scaler</code> for DNP3 slave to Modbus master conversion. The analog inputs received from the RTU are divided by the scaler before conversion to SCADA protocol. Previously only DNP3 to IEC104 supported.			7278
	AI scaler now supports both divisor and multiplier			7506
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	iecd	port	ai_scaler_op	
Critical process support for IECD	IECD now added to list of critical processes that are automatically restarted			7294

DNP3 group 40 analog output variation	Added support for DNP3 slave group 40 analog output variation			7548
	Package	Section	Options	
	iecd	port	dnp3s_g40_variation	
DNP3 relay type	Support new configuration option for specifying command point relay type			7512
	Package	Section	Options	
	iecd	cmdpoint	dnp3_relay_type	
IEC101RTR TCP Server Mode	Support TCP Server Mode for IEC101RTR IEC101 connection			6992
	Package	Section	Options	
	iecd	link101	listen_ip, listen_port	
IEC104 command point IOA	New configuration option for IEC104 master command point information object address			7579
	Package	Section	Options	
	iecd	cmdpoint	iec104m_cmd_ioa	
IEC104 to DNP3 double command conversion	New option values [4 5] added to <code>iecd.port.dnp3_app_output_mode</code> option that determine behaviour when an IEC104 command with S/E bit is received			7423
MQTT Azure DPS	Added support for MS Azure's IOT hub Device Provisioning Service (DPS)			7028
	Package	Section	Options	
	iecd	port	see user manual	
MQTT read specific data point	MQTT can now be configured to read specific data points			
Modbus bitmap	Support bitmap handling in Modbus master			7371 7473
	Package	Section	Options	
	iecd	point	mb_bitmask	
Modbus data formats	Extend supported data format values for MODBUS data points			6890
	Package	Section	Options	
	iecd	point	mb_data_fmt; modbus_data_fmt	
Modbus DI inversion	Support DI inversion for Modbus master			7507
Modbus dual data point handling	Support dual data and command point handling for IEC104 slave to Modbus master conversion. Two Modbus registers can now be converted into a single DPI			7475
	Package	Section	Options	
	iecd	port	modbus_dual_io; modbus_index2	
Modbus frame retransmit counter	Added configuration for MODBUS master frame retransmit count			
	Package	Section	Options	
	iecd	port	modbus_max_retries	
New VHMI payload types	Add support for sending publish messages via MQTT using different payload formats			
	Package	Section	Options	
	iecd	port	vhmi_mqtt_payload_fmt; vhmi_mqtt_client_name; vhmi_mqtt_site_name	

SCEP				
TPM support	SCEP now supports key pair management in TPM			7125
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	strongswan	scep_cert	use_tpm; key_label	
SNMP				
Multiwan state OID	Added ifMultiwanState to VA-UCI-MIB			6915
Sim detection OID	Added SimIn to VA-MODEM-MIB			6915
SSH				
Limit concurrent users	Support new option for limiting concurrent authenticated user sessions (Mantis: 7160)			7160
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	dropbear	dropbear	MaxConnections	
Strongswan				
IKEv2 Multiple subnet support	Support multiple subnets for ikev2			6026
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	strongswan	connection	locallanextra; remotelanextra	
TPM support	Support strongswan keys in TPM. TPM keys are supported via the <code>token</code> secret type. In this case the value of the secret specifies the label of the key to use.			4460
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	strongswan	secret	secrettype 'token'; secret '<TPM-label>'	
XAuth EAP support	Added support for xauth-eap and eap-radius authentication methods			6294
	<u>Package</u>	<u>Section</u>	<u>Options</u>	
	strongswan	connection	localauth; localauth2; remoteauth; remoteauth2	
		radius_server	enabled; address; secret; auth_port; acct_port	
System				
Busybox	Enable support for <code>who</code> command			6788
Firmware	Prohibit downgrading router firmware on models using Sierra Wireless Toshiba NAND flash to an unsupported version (< 25.03.43.014)			7488
Syslog	New warning message generated to local and remote syslog when any entries stored locally are discarded due to log rotation (Mantis: 7162)			7162
Terminal Server				
Show configuration CLI command	Added support for display of running terminal server configuration CLI command			6893
	<code>cli: show config</code>			
VA Events				

VA Event System now supports ieee8021x event class and events				
802.1x events	<u>Id</u>	<u>Name</u>	<u>Severity</u>	<u>Event Template</u>
	1	IEEE8021xRestrictingIf	notice	IEEE8021x restricting on % {p1}
	2	IEEE8021xAllowingAllonIf	notice	IEEE8021x allowing all on % {p1}
	3	IEEE8021xAllowingMAConIf	notice	IEEE8021x allowing % {p1} on % {p2}
	4	IEEE8021xBlockingMAConIf	notice	IEEE8021x blocking % {p1} on % {p2}
	6528			
Web UI				
Disable web UI	Added new option to disable web UI			
	<u>Package</u>	<u>Section</u>	<u>Options</u>	7068
	uhttpd	main	webui_enabled	
Limit concurrent users	Support new option for limiting concurrent user sessions			
	<u>Package</u>	<u>Section</u>	<u>Options</u>	7161
	luci	sauth	sessionlimit	
LTE band display	Show supported LTE bands for enable/disable via Web UI. web: services->mobile manager->lte			
Session control	Added utility to list and terminate web sessions (Mantis: 7159)			
	web: system->sessions cli: sessionctl			7159
Web UI theme	New restructured web UI with navigation links on left side frame.			
WeConnect				
DCU VPN Concentrator Support	Added support for DCU VPN Concentrator to WeConnect			

10.6Release 25.03.43.014

General	
Sierra Wireless	Added support for new Sierra Wireless NAND flash (Toshiba TC58NYG2S0H). Note: Routers running this Sierra Wireless flash version require v2.6 bootloader and cannot be rolled back to firmware prior to 25.03.14.014.

10.7Release 25.03.43.009

Certificates

Check both TPM and flash for certificate key	<p>If the key cannot be found in the location specified in the configuration file, the router will automatically check an alternate location using the following methodology (Mantis: 6820).</p> <ul style="list-style-type: none"> When configured for PEM key and key cannot be found at the configured location, the router will try to use a TPM key with name corresponding to base file name (/etc/uhttpd.key -> "uhttpd"). When configured for TPM key and key cannot be found in the TPM, the router will try to use file "/etc/<tpm label>.key" 						
Mobile							
FOTA support for Unitac modules	Support FOTA upgrade for Unitac modules						
Neighbour cell information	<p>Added display of neighbouring cell information. Currently only supported on Unitac ML620/660 and Quectel EC200x series</p> <pre>cli: vam -n</pre>						
Sierra Wireless WP7702 LTE-M support	Added support for Sierra Wireless WP7702 LTE-M1/NB1 mobile module on Merlin series						
Multiwan							
Multiwan upper retry limit for roaming interfaces	<p>For 3G roaming connections, and connections with <code>retry_on_first_fail</code> enabled, to avoid getting stuck on one SIM, a new Multiwan configuration parameter defines the maximum number of seconds to stay with an interface after its first failure before proceeding. (Mantis: 6975)</p> <pre>cli: multiwan.interface.retry_connection_max_sec (def: multiwan.interface.ifup_timeout_sec)</pre>						
Power over Ethernet							
PoE port stop/start	<p>Power over an individual Ethernet port can now be stopped and started via the PoE status page on the web UI (Mantis: 6827)</p> <pre>web: status->PoE</pre>						
SCADA							
DNP3 Analog Set point command variation	<p>Added new option for DNP3 Analog Set point command variation</p> <table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>iecd</td> <td>cmdpoint</td> <td>dnp3_cmd_variation (def: 0)</td> </tr> </tbody> </table>	Package	Section	Options	iecd	cmdpoint	dnp3_cmd_variation (def: 0)
Package	Section	Options					
iecd	cmdpoint	dnp3_cmd_variation (def: 0)					
MODBUS to Remote IO protocol conversion	Added support for MODBUS to Remote IO (ioservd) protocol conversions (Mantis: 6886)						
Update IEC104 master on DNP3 static variation change	<p>Added new feature to transmit a spontaneous update to IEC104 master on DNP3 static variation value change</p> <table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>iecd</td> <td>port</td> <td>dnp3_tx_spont_on_static_change (def: 0)</td> </tr> </tbody> </table>	Package	Section	Options	iecd	port	dnp3_tx_spont_on_static_change (def: 0)
Package	Section	Options					
iecd	port	dnp3_tx_spont_on_static_change (def: 0)					
TPM							

List TPM keys	Support new diagnostic command to list TPM keys <code>cli: tpm-cli listkeys</code>
---------------	---

10.8Release 25.03.43.000

General							
Merlin4100 support	Added support for Merlin4100 series						
GPS							
GPS MIB support	Added support for <code>VA-GNSS-MIB</code> for retrieval of GPS values						
Network							
Dummy interface support	Added support for dummy interfaces. Dummy interfaces are real kernel interfaces (unlike alias interfaces) and support all the configuration options of a static interface. Dummy interfaces are useful in combination with VRFs as they can be isolated from general routing.						
Ignore carrier state option	Support new option for static protocol interfaces to ignore carrier state changes. This allows interfaces to stay permanently up even when physical connection is not present (Mantis: 6739)						
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>network</td> <td>interface</td> <td>ignore_carrier_state (def: no)</td> </tr> </tbody> </table>	Package	Section	Options	network	interface	ignore_carrier_state (def: no)
Package	Section	Options					
network	interface	ignore_carrier_state (def: no)					
System							
IP PAD support	Added <code>padd</code> and <code>vald</code> packages for IP PAD support for converting legacy X.25 serial communication over TCP/IP.						
SCADA							
MODBUS to Remote IO protocol conversion	Added support for MODBUS to Remote IO (<code>ioservd</code>) protocol conversions (Mantis: 6886)						
Serial to UDP multi-point mode	Added support for multiple UDP peers on serial port. Data received on a serial port is transmitted to all peers; data received from any peer is transmitted on the serial port. Up to 8 UDP peers supported (Mantis: 6723)						
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>tservd</td> <td>port</td> <td>udpMultiPointOn (def: no); remote_ipX; udpRemotePortX</td> </tr> </tbody> </table>	Package	Section	Options	tservd	port	udpMultiPointOn (def: no); remote_ipX; udpRemotePortX
Package	Section	Options					
tservd	port	udpMultiPointOn (def: no); remote_ipX; udpRemotePortX					

10.9Release 25.03.23.000

Roaming Manager	
-----------------	--

	Added new connection retry options for Roaming Manager feature		
Roaming Manager connection retry options	Package	Section	Options
	network	interface	roaming_link_success_time (def: 600 secs); roaming_prefer_best_operator (def: no); roaming_scan_inheritance (def: no)
	multiwan	interface	retry_on_first_fail (def: no)
SCADA			
	Added support for MODBUS TCP routes (Mantis: 6643)		
MODBUS TCP routes	Package	Section	Options
	iecd	mbtcp_route	ifnum; devaddr, ipaddr
	Support for cyclic transmission of data point messages		
IECD104 Slave cyclic transmission	Package	Section	Options
	iecd	port	iecd104_cyclic_on (def: 0)
Transparent mode offline queue	Added support for IEC104 slave offline queue when using transparent mode (no iec104s application layer)		
	Support for binding IEC104 Slave socket to a VRF for isolation from general routing (Mantis: 4802)		
VRF	Package	Section	Options
	iecd	port	iecd104_ip1_vrf; iec104_ip2_vrf; iecd104_ip3_vrf; iec104_ip4_vrf; iecd104_ip5_vrf; iec104_ip6_vrf;
System			
	Added support for time update via GNSS.		
GNSS time synchronisation	Note: Router requires GNSS capabilities and GNSS is enabled (Mantis: 6229)		
	Package	Section	Options
	system	timeserver	gnss_clock_source_enabled (def: no)

10.10 Release 25.02.99.000

Mobile	
FOTA upgrade via CURL	FOTA upgrade can now use CURL to download a firmware image from remote location
SCADA	
IECD61850 Slave to MODBUS Server	Added support for IEC61850 slave to MODBUS Server
IEC62351-3 TLS - CRL/OCSP Automated Fetching	Added support for CRL/OCSP automatically fetching from a link provided within the certificate. Previously implementation only used a local file (Mantis: 5955)
New IECD diagnostics	Added new command line diagnostics to show all possible point and cmdpoint options (Mantis: 6556) cli: iecd show point options cli: iecd show cmdpoint options

10.11 Release 25.02.80.000

BGP			
BGP MIB support	Added BGP-4-MIB support so BGP information can be retrieved via SNMP (Mantis: 6347)		
FXS			
Analogue gain	Added options to store FXS card gain		
	<u>Package</u>	<u>Section</u>	<u>Options</u>
	fxs	interface	rx_analogue_gain (def: 0.0); tx_analogue_gain (def: 0.0)
General			
Merlin4400 support	Added support for Merlin4400 series		
Sierra Wireless	Added support for newer Sierra Wireless NAND flash. Note: Routers running newer Sierra Wireless flash cannot be rolled back prior to 25.02.80.000		
GPS			
GPS diagnostics	Added new <code>gps</code> diagnostics command		
SNMP			
LAPB MIB support	Added support for Virtual Access VA-LAPB-STATS-MIB which provides level 2 statistics for the serial interface (Mantis: 4695).		
Modem firmware version MIB support	Virtual Access VA-MODEM-MIB modemTable now supports <code>modemFirmwareVersion</code> and <code>modemGsmLtePci</code> (Mantis: 5912)		
VA roaming manager MIB support	Added MIB support for VA Roaming Manager (<code>vaRoamingManagerModule</code>) feature to VA-MODEM-MIB (Mantis: 5842)		
Mobile			
EID retrieval	Support EID retrieval for Quectel, Simcom, Sierra Wireless, Huawei and Telit mobile modules. EID information on the SIMs can be displayed using <code>vam -a</code> command (Mantis: 6236)		
FOTA upgrade	Support Quectel FOTA upgrade via locally stored file		
Monitor			
LTE band and cell diagnostics	Added support for LTE band and cell information in ISAD bins (Mantis 6007)		
VRF support for monitor keepalive	Added support for configuration of VRF domain for Monitor keepalive traps (Mantis: 5983)		
	<u>Package</u>	<u>Section</u>	<u>Options</u>
	monitor	keepalive	vrf
Multiwan			

Multiwan interface scanning timeout	New multiwan config parameter to extend <code>ifup</code> timeout when a mobile roaming operator scan is active. Used in conjunction with VA Roaming Manager feature, this parameter is added to the normal <code>ifup_timeout_sec</code> used for <code>ifup</code> operations whenever the <code>ifup</code> occurs during a 3G operator background scan, or the <code>ifup</code> itself triggers such a scan, on the modem being used for the current interface.						
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>multiwan</td> <td>interface</td> <td><code>ifup_scanning_timeout_sec</code> (def: 480 secs)</td> </tr> </tbody> </table>	Package	Section	Options	multiwan	interface	<code>ifup_scanning_timeout_sec</code> (def: 480 secs)
Package	Section	Options					
multiwan	interface	<code>ifup_scanning_timeout_sec</code> (def: 480 secs)					
SCADA							
DNP3 to IEC104 DI inversion and AI Scaling	Added support for inversion of single bit binary input points (Gr1, Gr2) for DNP3 RTU's to IEC104 Scada master. In addition, added support for a new option for analog scaling – the analog inputs received from the RTU are divided by the scaler before conversion to SCADA protocol (mantis: 6419)						
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>iecd</td> <td>port</td> <td><code>di_invert</code> (def: 0); <code>ai_scaler</code> (def: 0)</td> </tr> </tbody> </table>	Package	Section	Options	iecd	port	<code>di_invert</code> (def: 0); <code>ai_scaler</code> (def: 0)
Package	Section	Options					
iecd	port	<code>di_invert</code> (def: 0); <code>ai_scaler</code> (def: 0)					
Health points in multi master mode	Added support for health points (6) in multi-master mode						
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>iecd</td> <td>port</td> <td><code>iec104_rtuX_health_ioa</code>;</td> </tr> </tbody> </table>	Package	Section	Options	iecd	port	<code>iec104_rtuX_health_ioa</code> ;
Package	Section	Options					
iecd	port	<code>iec104_rtuX_health_ioa</code> ;					
HMI second interface	Added support for HMI Second Control Interface (MQTT)						
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>iecd</td> <td>port</td> <td><code>modbus_slave_devaddr</code>; <code>modbus_slave_protocol</code>; <code>modbus_slave_local_ip</code>; <code>modbus_slave_tcp_port</code> (def: 502); <code>modbus_slave_serial_ifnum</code>; <code>modbus_slave_use_tls</code>; <code>modbus_slave_tls_cacertfile</code>; <code>modbus_slave_tls_crlfile</code>; <code>modbus_slave_tls_certfile</code>; <code>modbus_slave_tls_keyfile</code>; <code>modbus_slave_tls_pass</code>; <code>modbus_slave_tls_common_name</code>; <code>modbus_slave_tls_validate_peer_cert</code>; <code>modbus_slave_tls_verify_depth</code>; <code>modbus_slave_tls_force_tls1_2</code>; <code>modbus_slave_tls_cipherlist</code></td> </tr> </tbody> </table>	Package	Section	Options	iecd	port	<code>modbus_slave_devaddr</code> ; <code>modbus_slave_protocol</code> ; <code>modbus_slave_local_ip</code> ; <code>modbus_slave_tcp_port</code> (def: 502); <code>modbus_slave_serial_ifnum</code> ; <code>modbus_slave_use_tls</code> ; <code>modbus_slave_tls_cacertfile</code> ; <code>modbus_slave_tls_crlfile</code> ; <code>modbus_slave_tls_certfile</code> ; <code>modbus_slave_tls_keyfile</code> ; <code>modbus_slave_tls_pass</code> ; <code>modbus_slave_tls_common_name</code> ; <code>modbus_slave_tls_validate_peer_cert</code> ; <code>modbus_slave_tls_verify_depth</code> ; <code>modbus_slave_tls_force_tls1_2</code> ; <code>modbus_slave_tls_cipherlist</code>
Package	Section	Options					
iecd	port	<code>modbus_slave_devaddr</code> ; <code>modbus_slave_protocol</code> ; <code>modbus_slave_local_ip</code> ; <code>modbus_slave_tcp_port</code> (def: 502); <code>modbus_slave_serial_ifnum</code> ; <code>modbus_slave_use_tls</code> ; <code>modbus_slave_tls_cacertfile</code> ; <code>modbus_slave_tls_crlfile</code> ; <code>modbus_slave_tls_certfile</code> ; <code>modbus_slave_tls_keyfile</code> ; <code>modbus_slave_tls_pass</code> ; <code>modbus_slave_tls_common_name</code> ; <code>modbus_slave_tls_validate_peer_cert</code> ; <code>modbus_slave_tls_verify_depth</code> ; <code>modbus_slave_tls_force_tls1_2</code> ; <code>modbus_slave_tls_cipherlist</code>					
IOSRVD direct serial comms	Support IOSRVD interface to serial using direct driver calls instead of UNIX sockets to <code>tserverd</code> (Mantis: 6322)						
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>iecd</td> <td>port</td> <td><code>modbus_serialX_mode</code>; <code>modbus_serialX_speed</code>; <code>modbus_serialX_wsize</code>; <code>modbus_serialX_parity</code>; <code>modbus_serialX_stops</code> (where X is 0 or 1)</td> </tr> </tbody> </table>	Package	Section	Options	iecd	port	<code>modbus_serialX_mode</code> ; <code>modbus_serialX_speed</code> ; <code>modbus_serialX_wsize</code> ; <code>modbus_serialX_parity</code> ; <code>modbus_serialX_stops</code> (where X is 0 or 1)
Package	Section	Options					
iecd	port	<code>modbus_serialX_mode</code> ; <code>modbus_serialX_speed</code> ; <code>modbus_serialX_wsize</code> ; <code>modbus_serialX_parity</code> ; <code>modbus_serialX_stops</code> (where X is 0 or 1)					
IOSRVD MQTT	Added support for remote IO and MQTT slave (Mantis: 6315)						
MODBUS master side analog filtering	When IECD is configured to communicate with a modbus slave, it can receive updates of register values that are modelling analog inputs (Holding Registers and/or Input Registers). Since analog values can be 'noisy' in nature, these updates can be quite frequent. If it is desired to limit the frequency of these updates, it is now possible to apply per data point filtering of analog values.						
	<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>iecd</td> <td>point</td> <td><code>modbus_filter_mode</code>; <code>modbus_filter_db_val</code>; <code>modbus_filter_sampling_time_secs</code>; <code>modbus_filter_transmit_time_secs</code></td> </tr> </tbody> </table>	Package	Section	Options	iecd	point	<code>modbus_filter_mode</code> ; <code>modbus_filter_db_val</code> ; <code>modbus_filter_sampling_time_secs</code> ; <code>modbus_filter_transmit_time_secs</code>
Package	Section	Options					
iecd	point	<code>modbus_filter_mode</code> ; <code>modbus_filter_db_val</code> ; <code>modbus_filter_sampling_time_secs</code> ; <code>modbus_filter_transmit_time_secs</code>					

MODBUS slave to Modbus master TCP data conversion	Support Modbus slave to Modbus master TCP conversion (Mantis: 6047)		
	Package	Section	Options
	iecd	port	modbus_slave_devaddr; modbus_slave_protocol; modbus_slave_local_ip; modbus_slave_tcp_port (def: 502); modbus_slave_serial_ifnum; modbus_slave_use_tls; modbus_slave_tls_cacertfile; modbus_slave_tls_crfile; modbus_slave_tls_certfile; modbus_slave_tls_keyfile; modbus_slave_tls_pass; modbus_slave_tls_common_name; modbus_slave_tls_validate_peer_cert; modbus_slave_tls_verify_depth; modbus_slave_tls_force_tls1_2; modbus_slave_tls_cipherlist
MQTT offline queue	Added support for MQTT offline message queue for storing publish messages in memory while MQTT broker is offline.		
	Package	Section	Options
	iecd	port	mqtt_offline_q_on (def: 0)
MQTT payload logging	Added payload logging for MQTT publish (Mantis: 6317)		
	Package	Section	Options
	iecd	port	mqtt_debug_on (def: 0)
MQTT Slave to Modbus conversion	Added support for MQTT slave to Modbus protocol conversion (Mantis: 6319)		
RTU test emulator	Added support for VRTU (RTU Test Emulator) for pre-production SCADA connectivity and operations testing (Mantis: 6225)		
	Package	Section	Options
	iecd	port	virtu_simulation_interval_sec (def: 30)
Windows file format data point import	Support windows .xlsx extension for data point files import (Mantis: 6027)		

10.12 Release 25.02.14.032

No new features

10.13 Release 25.02.14.027

General	
Merlin4600 Sierra Wireless WP7609-G support	Due to differing versions of Sierra Wireless WP7609G Australia module this release marks official support for WP7609G in Merlin4600 series (Mobile code: PFJ) for all versions. Note: Do not downgrade the Merlin4600 (PFJ) variant to firmware prior to SXL-25.02.14.027.
Mobile	
EID retrieval using SIMCOM 7070E	The SIMCOM 7070E mobile module can now report EID information on the SIMs using vam -a command (Mantis: 6236)

LTE-450 mobile module support	Merlin4600 series now supports an alternate mobile module via PCIe slot in order to support frequency bands not support by the on board Sierra Wireless radio, in particuar LTE-450 bands 31, 72 and 87 using Unitac and SIMCOM 7070E modules.
-------------------------------	--

10.14 Release 25.02.14.016

DI/DO							
Digital Input	Merlin4600 series digital input values changed to match GW2020 series for compatible SCADA operation						
	<table border="1"> <thead> <tr> <th>Input value</th> <th>State</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>Input not detected / open / low</td> </tr> <tr> <td>1</td> <td>Input detected / closed / high</td> </tr> </tbody> </table>	Input value	State	0	Input not detected / open / low	1	Input detected / closed / high
Input value	State						
0	Input not detected / open / low						
1	Input detected / closed / high						

10.15 Release 25.02.14.013

Ethernet															
Ethernet port to interface mapping using port names	<p>Ethernet interface configuration now uses driver port names in option ifname rather than <code>va_switch</code> configuration section for mapping interfaces to Ethernet ports. The <code>va_switch</code> method used in other hardware models is now deprecated for Merlin4600 series. Use space separator when specifying multiple port names in option ifname.</p> <p>When bridging Ethernet ports option type must be set to 'bridge' (Mantis 6028)</p> <table border="1"> <thead> <tr> <th>Physical port label</th> <th>network.interface ifname value</th> </tr> </thead> <tbody> <tr> <td>Ethernet A</td> <td>portA</td> </tr> <tr> <td>Ethernet B</td> <td>portB</td> </tr> <tr> <td>Ethernet C</td> <td>portC</td> </tr> <tr> <td>Ethernet D</td> <td>portD</td> </tr> <tr> <td>SFP I</td> <td>portI</td> </tr> <tr> <td>SFP J</td> <td>portJ</td> </tr> </tbody> </table> <p>Example bridged configuration:</p> <pre>package network config interface 'LAN' option ifname 'portA portB portC portD' option type 'bridge'</pre> <p>Example segmented configuration:</p> <pre>package network config interface 'LAN1' option ifname 'portA portB portC' option type 'bridge' config interface 'LAN2' option ifname 'portD'</pre>	Physical port label	network.interface ifname value	Ethernet A	portA	Ethernet B	portB	Ethernet C	portC	Ethernet D	portD	SFP I	portI	SFP J	portJ
Physical port label	network.interface ifname value														
Ethernet A	portA														
Ethernet B	portB														
Ethernet C	portC														
Ethernet D	portD														
SFP I	portI														
SFP J	portJ														

SCADA

Allow commands to work without status points Setting option `iec104_status_ioa` in a `cmdpont` section to 0 makes the IEC104 ignore the feedback point, but the commands still work. (Mantis: 5981)

IEC104 Double Bit command conversion to two DNP3 single commands Setting option `iec104_status_ioa` in a `cmdpont` section to 0 makes the IEC104 ignore the feedback point, but the commands still work. (Mantis: 5981)

IEC104 multi master support The IEC104 slave now supports up to 6 SCADA masters that can control the same RTU. In a normal scenario there is a single IEC104 SCADA master connecting to the router. It may sometimes use several TCP concurrent connections, however only one connection is active and transferring data at a time. All configured data points are sending data to the same connected IEC104 master.

In some scenarios it may be necessary that several IEC104 SCADA masters are polling and controlling the same RTU concurrently. Moreover, it may be desirable that one master polls or receives data from a specific set of data points (identified by IOAs (information object addresses)) while another master polls a different set of data points within the same RTU. (Mantis: 6012)

Package	Section	Options
iecd	port	<code>iec104_multi_master_on</code> (def: 0); <code>iec104_conn1_casdu</code> ; <code>iec104_conn2_casdu</code> ; <code>iec104_conn3_casdu</code> ; <code>iec104_conn4_casdu</code> ; <code>iec104_conn5_casdu</code> ; <code>iec104_conn6_casdu</code> ; <code>iec104_local_ip1</code> ; <code>iec104_local_ip2</code> ; <code>iec104_local_ip3</code> ; <code>iec104_local_ip4</code> ; <code>iec104_local_ip5</code> ; <code>iec104_local_ip6</code> ; <code>iec104_local_tcpport1</code> ; <code>iec104_local_tcpport2</code> ; <code>iec104_local_tcpport3</code> ; <code>iec104_local_tcpport4</code> ; <code>iec104_local_tcpport5</code> ; <code>iec104_local_tcpport6</code>
	point	<code>iec104_conn_mask</code>
	cmdpont	<code>iec104_conn_mask</code>

Modbus HMI support VHMI (Virtual HMI) is a human machine interface exposed to an externally connected software. Current version supports only Modbus TCP protocol for the connection to the HMI software. The router acts as a Modbus TCP slave/server. External HMI software is a Modbus TCP master/client. When VHMI is enabled, the Modbus TCP client can poll the values of all data point objects in parallel to normal protocol conversion process. (Mantis: 6040)

Package	Section	Options
iecd	port	<code>vhmi_enabled</code> (def: 0); <code>vhmi_proto</code> (def: <code>modbus_tcp</code>); <code>vhmi_listen_port</code> (def: 502); <code>vhmi_debug_on</code> (def: 0)
	point	<code>vhmi_on</code> (def: 0); <code>vhmi_regaddr</code> (def: 0); <code>vhmi_dword</code> (def: 0)

Support CP24 timestamp format messages in IEC101 to 104 conversion	IEC101 Type ID 2, 4, 6, 8, 10,12,14,16 now supports CP24Time2a (Mantis: 5980)						
Support Regulating Step and Bitstring commands for IEC101 to IEC104 conversion	Added IEC101 to IEC104 conversion support for commands (Mantis: 6030): <ul style="list-style-type: none"> C_RC_NA_1 Regulating step C_BO_NA_1 Bitstring of 32 bit 						
Strongswan							
SCEP certificate debug level	The SCEP client natively supports debug options with 4 levels levels - 0,1,2,3 and 4. These can now be configured using new config option <code>debug_level</code> . Set to 0 to disable. (Mantis 5881)						
<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>strongswan</td> <td>scep_cert</td> <td>debug_level (def: 0)</td> </tr> </tbody> </table>		Package	Section	Options	strongswan	scep_cert	debug_level (def: 0)
Package	Section	Options					
strongswan	scep_cert	debug_level (def: 0)					
SCEP cert user option	New SCEP config option user which is the high-level concept of the user of the cert. It gets read access via its group. The owner is root, the group is the user. The user is expected to be a member of its group. User certs are stored in <code>/etc/certs</code> tree (Mantis: 5913).						
<table border="1"> <thead> <tr> <th>Package</th> <th>Section</th> <th>Options</th> </tr> </thead> <tbody> <tr> <td>strongswan</td> <td>scep_cert</td> <td>user (def: strongswan)</td> </tr> </tbody> </table>		Package	Section	Options	strongswan	scep_cert	user (def: strongswan)
Package	Section	Options					
strongswan	scep_cert	user (def: strongswan)					

10.16 Release 25.02.14.002

No new features

10.17 Release 25.02.14.000

Hardware	
Digital IO	Support for <ul style="list-style-type: none"> Six digital input ports with Wet/Dry control Two digital outputs <p>An event is raised in the router's syslog when the status of the digital input changes. The routers event system can be used to forward the events to a Syslog Server, SNMP, email or SMS.</p>
SFP	Support for two 1Gbps SFP ports using physical ports I and J. Ports can operate with Ethernet or Fibre adapters and are internally configured as standard Ethernet interfaces

Trusted Platform Module (TPM)	<p>A Trusted Platform Module (TPM) is a microcontroller-based chip, which provides hardware-based security for the user's data, cryptographic keys, and safeguards confidential information.</p> <p>The Merlin hardware comes with a set of keys that are burned to the TPM's memory fuse and cannot be changed. These keys are used to produce a set of keys that act as local Root of Trust. These can then be used by a variety of system processes and for data exchanges. This digital signing process ensures the highest level of identity verification.</p>
-------------------------------	---

SNMP

Last Gasp	Power fail event generated in syslog and optionally delivered using the routers event system via an SNMP trap when power is lost.
-----------	---

SCADA

SCADA applications	Support for SCADA protocol conversion suite.																								
	<table border="1"> <thead> <tr> <th>Web</th> <th>Package</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>DNPOSD</td> <td>dnposd</td> <td>DNPOSD is a SCADA application which emulates a DNP3 controlled station and presents status of monitored interfaces and device information as DNP3 objects</td> </tr> <tr> <td>IEC101MON</td> <td>iec101mon</td> <td>IEC101MON is a router application that monitors IEC 60870-5-101 link and forwards the decoded messages over MQTT</td> </tr> <tr> <td>IEC101RTR</td> <td>iec101rtr</td> <td>IEC101RTR is a SCADA protocol conversion application which acts as IEC101 Slave and converts SCADA traffic to IEC104 Master</td> </tr> <tr> <td>IECD</td> <td>iecd</td> <td>IECD is a SCADA protocol conversion application supporting many SCADA protocols: IEC 60870-5-104, IEC 60870-5-101, IEC61850, DNP3, Modbus, MQTT</td> </tr> <tr> <td>IOSRVD</td> <td>iosrvd</td> <td>IOSRVD is a router application working with IECD to communicate to Remote IO devices</td> </tr> <tr> <td>Modbus Gateway</td> <td>modbus_gw</td> <td>Modbus Gateway SCADA protocol conversion application which acts as Modbus Slave and converts SCADA traffic to IEC104 Master</td> </tr> <tr> <td>RTUD</td> <td>rtud</td> <td>RTUD allows the remote SCADA master to monitor and control the digital IOs of the Virtual Access router that acts as the RTU slave. RTUD supports IEC 60870-5-104, DNP3 and Modbus.</td> </tr> </tbody> </table>	Web	Package	Description	DNPOSD	dnposd	DNPOSD is a SCADA application which emulates a DNP3 controlled station and presents status of monitored interfaces and device information as DNP3 objects	IEC101MON	iec101mon	IEC101MON is a router application that monitors IEC 60870-5-101 link and forwards the decoded messages over MQTT	IEC101RTR	iec101rtr	IEC101RTR is a SCADA protocol conversion application which acts as IEC101 Slave and converts SCADA traffic to IEC104 Master	IECD	iecd	IECD is a SCADA protocol conversion application supporting many SCADA protocols: IEC 60870-5-104, IEC 60870-5-101, IEC61850, DNP3, Modbus, MQTT	IOSRVD	iosrvd	IOSRVD is a router application working with IECD to communicate to Remote IO devices	Modbus Gateway	modbus_gw	Modbus Gateway SCADA protocol conversion application which acts as Modbus Slave and converts SCADA traffic to IEC104 Master	RTUD	rtud	RTUD allows the remote SCADA master to monitor and control the digital IOs of the Virtual Access router that acts as the RTU slave. RTUD supports IEC 60870-5-104, DNP3 and Modbus.
Web	Package	Description																							
DNPOSD	dnposd	DNPOSD is a SCADA application which emulates a DNP3 controlled station and presents status of monitored interfaces and device information as DNP3 objects																							
IEC101MON	iec101mon	IEC101MON is a router application that monitors IEC 60870-5-101 link and forwards the decoded messages over MQTT																							
IEC101RTR	iec101rtr	IEC101RTR is a SCADA protocol conversion application which acts as IEC101 Slave and converts SCADA traffic to IEC104 Master																							
IECD	iecd	IECD is a SCADA protocol conversion application supporting many SCADA protocols: IEC 60870-5-104, IEC 60870-5-101, IEC61850, DNP3, Modbus, MQTT																							
IOSRVD	iosrvd	IOSRVD is a router application working with IECD to communicate to Remote IO devices																							
Modbus Gateway	modbus_gw	Modbus Gateway SCADA protocol conversion application which acts as Modbus Slave and converts SCADA traffic to IEC104 Master																							
RTUD	rtud	RTUD allows the remote SCADA master to monitor and control the digital IOs of the Virtual Access router that acts as the RTU slave. RTUD supports IEC 60870-5-104, DNP3 and Modbus.																							

Security

Last Gasp	Power fail event generated in syslog and optionally delivered using the routers event system via an SNMP trap when power is lost.
-----------	---

WeConnect

WeConnect	<p>WeConnect allows secure remote access to both the network behind the devices and the devices themselves. WeConnect solves the complexity of managing VPNs over the Internet. With WeConnect users can easily and securely connect to any IP-device on the network using their normal PC, smartphone or tablet.</p> <p>If you do not yet have an account, contact your local Westermo reseller or visit weconnect.westermo.com for further information.</p>
-----------	---

11 Appendix 2: Problems resolved history

11.1 Release 25.05.24.000

Module	Short Description	Mantis
Cwatch	Ensure a minimum of ICMP attempts when jitter and latency checks are enabled – 3 for jitter, 2 for latency	8095
	Fix segfault when an additional cwatch config section is empty	8554
	Log an error message when trying to restart a Sierra Wireless WP7xxx modules using cwatch radio module restart recipe as this module does not support	8398
	Show cwatch status info even when cwatch process is not running	8554
	Use parallel ping when multiple <code>icmp_hosts</code> defined	7312
DHCP Client	Fix DHCP client intermittently not installing the default route on a when ports are bridged	8823
Dropbear	Fix dropbear intermittently failing to start on an interface	8502
	Pass default key file to Dropbear and skip loading all other keys to avoid auth warning messages in syslog	8174
Ethernet	Fix broken Ethernet operation in Merlin series when upgrading Merlins using legacy <code>va_switch</code> config_section for mapping the Ethernet ports	8960
	Fix manual <code>ifup</code> on non auto Ethernet and SFP interfaces	8507
	Support <code>network.va_switch</code> config section on DSA platforms	8451
Event System	Fix <code>ConfigChanged</code> event not being generated when using configuration audit	7132
Failsafe	Fix auth error messages in syslog when console disabled using failsafe feature	8401
Firewall	Optimise local IP checking using cache	8307
IECD	Improve IECD launch speed when using a large number of data points	8608
	Set Point configuration defaults after importing points from CSV file	8301
	Sort command points and data points from lowest to highest in <code>iec show stats</code>	8701
IECD/DNP3	Fix display of DNP3S uplink time in <code>iec show stats</code>	8417
	Fix DNP3S event queue handling so the event queue persists across the uplink up and down events	8931
	Fix incorrect reporting of DNP3S link status	8620
	Fix support for DNP3 Group 3 data point (double bit binary input)	8597
	Fixed incorrect conversion of DNP3 G42 variation 6 events to IEC104 TI 36	8527
IECD/IEC104	Added Command Type ID validation to configured cmdpoint type id for IEC104S	8579
	Fix issues with IEC104 command point pass through dependencies	8617
	Improvements for IEC104 Server transmission queue for optimal upload performance.	8625
IECD/IEC61850	Added default config values for IEC61850 master settings	8351

	Fix an issue in SCL parser - converting DPS point types	8535
	Fix errors in mapping of IEC61850 DPS to IEC104 double point	8483
	Fix IEC61850M Read Instant Value option operation. <code>iec61850m readinst</code> option moved from <code>61850m</code> config section to global config section so it is applied to all points during SCL import	8574
	Fix IEC61850M SCL parser issue related to RCBs and datasets	8716
	Fix incorrect handling of IEC61850 DPC data type by the IEC61850 client	8493
	Fix incorrect reading of APC value	8497
	Fix issue in handling Point Invalid bit when multiple IEC61850M sessions are connecting	8353
	Fix issues in IEC61850M SCL file parser when dealing with multiple Logical Nodes	8482
	Fixed incorrect processing of INS variable during dataset poll	8794
	Fixed reading IEC61850 analog inputs (instantaneous vs averaged values)	8293
	Incomplete Parsing of Data and Command Points for 30 61850M Links	8570
	Set <code>iec104_sbo</code> parameter based on the parsed value of <code>ctrlmodel</code> of IEC61850M SCL file	8467
	Fix IEC61850M reports trigger options handling	8872
IECD/Modbus	Added display of point value for MQTTS to Modbus point display in <code>iecd show points</code> command	8691
	Allow value of 0 for Modbus register address	8615
	Fix incorrect reporting of point online (quality status)	8619
	Fix reporting of offline status on Modbus read errors - now Modbus read errors result in associated point coming offline	8529
	Fixed handling of online status bits in DNP3S to Modbus mode	8408
IECD/MQTT	Added default setting of MQTT port for VHMI	8531
	Fixed incorrect reporting of point value by VHMI over MQTT	8946
	Send point updates to dedicated topics if configured web: <code>system->iecd->server protocol->configure mqtt->topic->Append Name to Monitor Topic</code> cli: <code>iecd.port.mqtt_add_ptname_to_mon_topic</code>	8971
LLDP	Fix LLDP description delivery to peer	8627
	Fix LLDP neighbour establishment	8595
Management Users	Fix management user <code>allowed_pages</code> handling	8225
Mobile	Disable VoLTE on SIMCOM7600 mobile module to avoid establishing an IMS bearer in selected networks	8405
	Ensure correct LTE bands are selected when switching SIMs	8893
	Ensure Quectel initialisation doesn't require unnecessary module reboots	8859
	Fix crash for Quectel modules when SIM2 in during boot and SIM1 inserted after boot	8529
	Fix ICCID collection when SIM1 empty and SIM2 inserted to allow mobile interface to start correctly	8934

	Fix intermittent Unitac module connection after FOTA upgrade from module firmware from V13 to V14	8814
	Fix manual <code>ifup</code> first attempt on Sierra Wireless WP76XX modules	7827
	Fix RM520 mobile module connectivity using RM520NGLAAR01A08M4G_01.200.01.200 firmware	8698
	Increase sleep between turning off and on of radio module from 1 to 2 seconds to support SIMCOM7070E on Merlin4400 series.	8661
Multiwan	Check if route exists before modifying to avoid modifying a route for an incorrect interface. Fix issue where multiwan is modifying/removing routes for interfaces that are	8282
	Clear contrack table when routes are changed to avoid stale connections	8256
	Fix issue restoring default gateway metric when interface recovers	8282
	Fix mobile interface losing IP address after USB restart via command line or via Connect Watch <code>Interface restart</code> failure action	8754
	Fix multiwan crash due to module separation	8435
	Fix multiwan pre-empt functionality (broken in 25.04.35.000)	8575
	Ping failure not recorded when pings dropped due to iptables rules	8545
Network	Remove IP address display if interface is down using <code>network_status</code> command	6763
OpenVPN	Fix multiple OpenVPN tunnel establishment without the need for process restart	8478
	Fix Openvpn tunnel interface failing to get IP address with TPM stored keys	8822
SCEP	Fix issue due to empty <code>cacert</code> option value that could cause SCEP to fail to pull certificate on <code>strongswan</code> reboot	8885
	Fix SCEP certificate enrolment failure using TPM-backed key	8441
	Fix system clock changing to certificate expiry time on certificate retrieval	8871
	Strongswan will now skip connections that require certs that are retrieved via SCEP should those certs not be available yet	8377
SFP	Fix bridging two SFP ports on Merlin4600 series	8651
SNMP	Firewall Zone drop event now available in <code>VA-TRAPS-G02</code> MIB file	8829
Strongswan	Fix <code>ipsec statusall</code> crash when multiple peers connect to a single connection with <code>remoteaddress</code> configured as <code>%any</code> and an unspecified <code>remotelan</code>	8785
	Fix strongswan file permissions for IPsec XAUTH with PAM	8802
Syslog	Fix <code>misc nmea</code> kernel error messages in syslog	8533
	Fix <code>tty</code> error messages when used on VM	8461
System	Ensure <code>/etc/passwd</code> is updated when option <code>linuxuser</code> is set to <code>no</code>	8171
	Ensure <code>/etc/rollback</code> directory is automatically created and fix rollback from active update to altconfig target	8621
	Factory reset from web UI when force password present in factory config forces user to reset password on next log on.	8974
	Fix configuration error message due to obsoleted <code>openvpn_recipes</code> package	8811

	Fix incorrect config file errors when running configuration sanity check <code>sanity_check.sh</code>	8732
	Improve firmware validation to cover both kernel and main image before flashing to altimage	2882
Web	Define link colour for dark mode	8099
	Do not show DLMSD or COSEM configuration if no serial interface present	8061
	Fix menu items when they don't fit the menu width	8546
	Fix web UI becoming unresponsive when HTTPS status page left open in browser	8695
Web/Administ ration	Fix TPM key upload via web UI	7874
	Remove Upload private keys to TPM button since now handled via Certificate Management page	8235
Web/AT Command Service	Enhancements to AT Command Service web configuration and refresh of AT service status to refresh every 5 seconds	8238
Web/Certifica tes	Fix typo on HTTPS Certificate label	8891
Web/ Connection Watch	Fix incorrect Connection Watch status display on web UI when there are underlying configuration issues	8569
Web/Cwatch	Ensure ICMP jitter options are only present on web UI when method <code>icmp</code> is selected	6973
	Fix cwatch status showing as disabled when enabled	8837
Web/HTTP Server	Remove configuration options that are not required from web UI, fix default values and split configuration into tabs	8397
Web/ Interfaces	Fix issue when creating an interface with a device already assigned to another interface	4072
	Fix RECONNECT button press stalling the web UI until the interface has finished connecting	8982
Web/IPSec	Fix crash when accessing Authentication tab on web UI	8582
	Fix IPSec status display for multiple child tunnels	8444
	Fix IPSec status page display after disabling IPSec	8844
	Fix misleading preshared key ID selector label	8349
	Fix to ensure connection tab labels contain correct tunnel names	8729
	Fix Web UI incorrectly saving default values for IPSec Connection Additional Local and Remote Auth options	8801
	IPSec status now refreshes every 5 seconds	8464
	Removed cert file upload from strongswan web UI – now handled on certificate management page.	8464
	Reordering of configuration into separate tabs and removal of certificate file upload. Certificates are now handled in dedicated Certificate Management page.	8464
	Strongswan connection setting no longer removed when disabled via the web UI	8828

Web/Mobile	Fix 3G roaming manager custom sort script option when Roaming Sort Order is <code>none</code>	8991
	Fix missing band selection in web UI for Hucom mobile module	8372
Web/ Multiwan	Fix multiwan configuration using web UI when <code>main</code> configuration section is missing in config	8569
	Multiwan now stops correctly when disabled via the web UI	8085
Web/Power Monitor	Fix web UI default value for power monitor enabled field	8633
Web/Rollback	Fix rollback configuration through web UI when no options exist in configuration	8621
Web/Scada	Add missing IEC61850 datasets and control block configuration	8696
	Add MQTT server option dependencies for MQTT Number of Control Vars and MQTT Payload Format configuration	8682
	Add note to Data point descriptive name field to inform of 39 character limit	8616
	Add reminder on web UI to save config when changes made on IECD pages	8052
	Added IEC61850 to RTU protocols list for IEC104 command point	8213
	Added missing DNP3 group3 point type to data point in the web UI	8330
	Added missing Echo enable configuration option for CRSD	8954
	Added missing IECD options to web UI	8764
	Added quality column and data point quality reporting to IECD status in web UI	8406
	Change <code>modbus_regtype</code> command type import from string to numerical	8684
	Changed MQTT TLS Verify Depth to a dropdown list instead of integer	8707
	Description changed to reflect the fact that IEC61850 SCL file import only works with SCADA side protocol set to IEC104	8353
	Fix configuration of IEC104 Auth Exp Key Wrap Algo option	8718
	Fix data polling delays for IEC61850M to IEC104S protocol conversion when using multiple RTUs with large number of data points	8672
	Fix display of Integrated Totals IEC104 type ID	8656
	Fix IEC104 Master Link 2 tab option visible when only Link 1 is enabled	8765
	Fix IEC104 W option description in IEC104_LINK. Was previously incorrectly labelled IEC104 K	8436
	Fix issue in converting 104 setpoint float to Modbus 64 bit commands	8655
	Fixed data points in IECD status page for MQTT	8688
	Fixed incorrect processing of Modbus bitmap point type for DNP3S case	8675
Fixed Modbus point quality not updating in web status	8662	
Fixed point event queue overflow for IEC61850M to IEC104S protocol conversion for data points greater than 127	8560	
IECD Slave changed to IECD Server	8894	
Implemented missing command conversion from IEC104 Setpoint Float to Modbus	8614	

	Moved IEC104 health point configuration from Multi-master mode tab to new Health tab	8686
	Remove popup warning prompts users to save configuration on subpage	8587
	Update description for IEC61850M Read Instant Value	8821
	Update descriptions for MQTT server options	8680
	Updated IEC104M point field descriptions	8480
Web/SCEP	Fix error on UI after certificate deletion	8997
	Fix SCEP client status showing correctly	8835
	Fix SCEP status display in the web UI	8835
	SCEP request now initiated after <i>Save & Apply</i> via the web UI	8377
Web/SSH	Fix host key algorithm description to note that only RSA algorithms are advertised by the SSH server when no algorithm is selected	7312
Web/Status	Added mobile overview and routing table to web UI status overview page	6965
	Ensure AT Command Service status is not present when disabled	8862
	Ensure Connection Watch status is not present when disabled	6966
	Ensure Data Usage status is not present when disabled	6966
	Ensure GNSS status is not present when disabled	8858
	Suppress link local IPv6 addresses in routing table overview	6965
Web/Terminal Server	Fix missing Terminal Server configuration in web UI using SXL firmware	8393
Web/UDS	Added missing 'none' value for script type to allow loading a pure text file	8989
	Do not remove blank lines from scripts	8990
	Support UDS gzip encoding configuration via web UI	8368
Web/VRRP	Fix 'Track Interface' configuration as <code>list</code> type for proper operation	8637
Web/Weconnect	Enforce entering required Weconnect parameters	8634

11.2Release 25.04.63.000

Module	Short Description	Mantis
BCP	Fix BCP crash upon receipt of IPv6 frame	8116
Data Usage	Fix data usage bringing down interface when monthly usage limit reached	7759
Event System	Fix missing interface names in VA event messages generated by the firewall using the <code>recent</code> option.	8037
	Fix syslog message sending to multiple IP address	8046
Firewall	Fix broken protocol values (<code>igmp</code> , <code>eigrp</code> , <code>ax.25</code> , <code>etherip</code> , <code>ipcomp</code> , <code>vrp</code> , <code>l2tp</code> , <code>isi</code> , <code>sctp</code> , <code>fc</code>) used by firewall option <code>proto</code>	7906
	Support <code>vrp</code> as valid protocol option	7906
	Truncate zone names > 12 chars to avoid breaking firewall	7791
GPS	Fix <code>gpspeek</code> location information	7980

	GPS error messaging improved by using error messages instead of error numbers	6660
GRE	Prevent starting GRE interface if parent interface is missing	8103
HTTP Client	Fix chunk size addition when reporting download status to Activator when using Chunky Downloads that could result in download failure	8023
IECD	Fix parsing of AI scaler when importing data points from CSV file	8199
	Improved data points CSV import feature	8191
IECD/ IEC104 Slave	Fixed issue with sending End of Initialization message in IEC104 slave	8233
IECD/ IEC61850	Fix description in the IEC61850 Slave side data point for DO field	8019
	Fixed TCP connection drop on IEC104 clock sync processing	8211
IECD/DNP3	Fix error in displaying DNP3 app status	8348
	Fixed incorrect link assignment when sending dual point cmd IEC104S to DNP3M	8390
	Fixed issue with DNP3 analog input scaler for IEC104 TIs 9,11	8347
	Fixed issues in applying scaler to negative MODBUS value for DNP3 to MODBUS protocol conversion	8207
	Fixed sending ACT CON and ACT TERM to Scada Master for IEC104 slave to DNP3 master protocol conversion	8348
IECD/Modbus	Fix DNP3S to Modbus conversion issues for <code>select operate</code>	7999
	Fixed bug in converting MODBUS HR register reads to DNP3S points (G30 and G40) mapped to same HR index	7999
	Fix incorrect conversion from Modbus DI or CO to IEC104 Slave DPI (Type ID 3)	8380
	Support Modbus Slave to IEC104 Master command conversion for Set Point Float	8182
IECD/MQTT	Added support for Type ID 20 for IEC101 to MQTT protocol conversion	8135
	Fixed incorrect conversion of IEC101 double points to MQTT	8126
	Fixed issues with converting MQTT to IEC104 Master TypeIDs 9, 13, 48 and 50	8176
L2TP	Fix L2TP initialisation	8035
	Fix privileges which left PPP in a bad state	8071
Mobile	Added error messages for failed connection attempts for Quectel modules in Ethernet mode	7899
	Corrected 5G technology codes so that they match with 3GPP 27.007 Release 16	7992
	Correctly identify Unitac ML620DE and ML620EU modules in diagnostics. Previously both identified as ML620EU.	8166
	Disable <code>va-mobile</code> and execute <code>AT+CFUN=0</code> before powering down SIMCOM7070 modem to avoid module not reinitialising on USB bus	7996
	Ensures signal strength and registration status information is refreshed as part of the check whether or not the radio module is registered with a PLMN and the signal strength is sufficient. Fixes connectivity issue when last reported signal strength was -113dBm or less.	7919

	Fix 5G SA mode on Quectel RM520N-GL mobile module	7975
	Fix connection for bands > 64 for Sierra Wireless WP7611 (PFP) module	8370
	Fix crash when band detection on Sierra Wireless WP76xx failed	8334
	Fix incorrect detection of registration status while in GPRS mode	7945
	Fix Sierra Wireless WP7702 (QFT) mobile module becoming unresponsive when configured for ICCID collection	8360
	Fix SIM slot 2 3V/5V issue on Merlin series with Sierra Wireless WP7611 processor	8142
	Fixes to ensure Unitac modules are initialised correctly	8093
	Generate error message and handling if no supported LTE bands have been detected on a mobile module	8370
	Improve the handling of +CREG responses so that it also handles CREG mode 2	7880
	Only toggle the RF disable line when module is not present on the USB bus to avoid issues with correct phy detection. This fixes issues with SIM7070E starting on boot.	8114
	Power cycle the SIMCOM7070E modem if it starts in EDL mode	8014
	Reset SIMCOM module authentication details to avoid using stored credentials when username/password not explicitly set in configuration	8013
	Set minimum firmware software version for Quectel EM060 module to prevent rollback to unsupported firmware	8088
	Stop flushing contrack table every time a mobile connection fails to reconnect	8277
Monitor	Fix Monitor SSH access for SLA uploads	8175
Multiwan	Fix issue where default gateway is lost on route change	8282
	Split multiwan route management, health check and state management into separate modules	8327
	Log multiwan shell commands at debug level	8332
Network	Fix Ethernet interfaces on Merlin series intermittently failing to restart after a network restart command	8120
	Fix link loss when changing from bridge to single port	7937
	<code>ifup/ifdown</code> now correctly validate the UCI interface name before execution	6276
OpenVPN	Fix support for multiple tunnels	8316
	OpenVPN interfaces are no longer deleted on <code>ifdown/network restart</code> event	7871
PPP	Allow PPP interface to be up without IP address	8229
	Fix option <code>record</code> support	8022
PPPoE	Fix PPPoE interface on an Ethernet port not automatically starting on boot	7924
	When PPPoE link is on a VLAN, it is no longer necessary to configure a dummy UCI interface for the underlying device in order for the VLAN to be created	7924

Roaming Manager	Ignore test operators in roaming scan	8001
SFP	Fix SFP interface correctly detecting state when using certain 1000base-X copper adapters that were not identifying when the Ethernet link was down	8152
SNMP	Fix SNMP support for BGP. Fixes bug introduced in 25.04.16.000	7938
Strongswan	Fix conntrack flushing for strongswan on tunnel change	8249
Syslog	Fix bad values intermittently generated using firewall recent option	8055
System	Suppress UCI error on <code>version -a</code> command if mobile module is not initialised	7984
TPM	Fix HTTPS when keys are stored in the TPM	7922
	Improve messaging to users during key existence checks	7567
VRRP	Fix VRRP transition when tracking mobile interface on Merlin series	8020
Web	Added Security-Policy-Header (CSP) to prevent clickjacking	8087
	Align reboot loading page with web UI theme	8036
	Change 'Modem configuration' to 'Mobile Manager Configuration'	7310
	Do not show PoE on hardware that does not support	6967
	Ensure lines are visible underneath the login fields	8072
	Fix formatting error messages in web UI	8255
	Fix interface colours after firewall zone update	8056
	Fix pixelated background images	8072
	Fix web UI crash when option <code>ifname</code> is missing from an interface	8050
	Remove welcome message from landing page	8072
Web/Administration	Removed hostname and Westermo logo and link from web UI log in page	8072
	Fix broken link on TPM cert upload page	8082
	Fix TPM key upload	7874
	Improvements to reboot scheduling	8125
Web/Firewall	Upload TPM key button is now removed for non-TPM boards	8086
	Add option to WebUi to raise va events on zone dropped/rejected traffic. <code>cli: firewall.zone.discard_event</code>	7769
	Ensure firewall zone names are no longer than 12 characters	7791
Web/GPS	Add option to select mobile device required to use GPS	7943
	Replace GPS with GNSS	
	Restore link to google maps	7403
Web/HTTP Server	Fix typo on web UI HTTP Server TPM Key Name	8079
Web/Interfaces	Align up/down indicator centrally	7988
	Fix unable to select SIM1 or SIM2 from mobile interface SIM configuration option	8007
	Fix network interface colours to reflect up/down status	6536

	Fix removal of dependent interfaces from configuration	8074
	Support default route and metric configuration on L2TP interfaces	8073
	Update interface pages to show firewall zones as colours	7988
	Allow configuration of an MTU higher than 1500 bytes	7534
Web/IEC104 Slave	Fix incorrect display of value for IEC104S to Modbus TI 9, 3 and HR, DI	8385
Web/IECD	Add debug options for IEC61850 to web UI	8215
	Fixed IECD application restarting correctly when Save & Apply button used and IEC61850 connection is active.	8214
Web/IPsec Status	IPsec status now displays multiple subnets for IKEv2	8352
Web/Mobile	Removed choice for selection of the assigned radio module. Radio selection is now done via the SIM slot selection.	7893
	Mobile status information on the web now automatically refreshes every 5 seconds	8272
	Fix error on Mobile Manager page when using RFD mobile module - Hucom (WeTelecom) WPD-600N	8358
Web/Real Time Graph	Only show UCI network interfaces on the Realtime Traffic screen	7946
Web/Status	Do not display 802.1x, CESOP, LLDP, Mobile IP ,ADSL on status tab unless configured	6966
Web/Strongswan	Elliptic curve Diffie-Hellman algorithms can now be configured via the web UI when using IKEv2	7730
Web/System	Do not show HMAC password algorithm as a configurable option on hardware that does not support a TPM	7895

11.3Release 25.04.16.000

Module	Short Description	Mantis
Data Usage	Fix mobile phy detection on data usage start using faster processors	7865
Ethernet	Fix Ethernet ports intermittently reflecting incorrect state when bridging	7795
Mobile	Fix band selection for SIMCom7070E module	7833
	Fix SIMCom7070E module establishing data connection	7821
	Fixes to ensure APN information is set properly for Sierra Wireless radio modules	7777
		7797
	Fixes to ensure the manual network operator selection is executed in the right order	7797
	Log a warning that GNSS is not supported for SIMCom7070E mobile module	7822
Monitor	Fix mobile phy detection on monitor start using faster processors	7863
		7864
Multiwan	Fix crash caused by incorrect mobile phy detection on start up using faster processors	7835
	Produce warning for interfaces that do not exist	7857

System	Replace invalid spaces in hostnames with '-' at run time	7829
TPM	Fix error message when <code>tpm-cli flush</code> command is executed twice in a row	6010
Web	Prevent capitalisation of configuration section names	7856

11.4 Release 25.04.13.000

Module	Short Description	Mantis
Mobile	Fix Sierra Wireless module FOTA upgrade CRC32 checksum calculation	7724
OpenVPN	Don't create new <code>linux</code> and <code>uci</code> interface on openvpn restart	7735
System	Fix minimum machtype firmware version checking	7717
		7722
		7714
	Fix misleading 'cannot find device' messages on network restart or <code>ifup</code>	7798
Web	Fix issue socket closing before HTTP data is complete which can result in UI not displaying correctly	6738
		7752
Web/Realtime Graphs	Fix display of Realtime Graphs for mobile interfaces <code>web: status->Realtime Graphs</code>	7029
WeConnect	Add missing <code>ripd</code> and <code>openvpn</code> packages during provisioning	7687
		7688
	Network status diagnostics now correctly show WeConnect interface IP address	7682

11.5 Release 25.04.08.000

Module	Short Description	Mantis
802.1x	Fix 802.1x authentication	4290
		7464
	Fix 802.1x restart after <code>ifup</code> or cable unplug/plug	7530
Activator	Fix issue with multiple downloads from different services (active update, inventory, audit) running simultaneously	6321
Boot	Improve power-on sequencing for USB hub on GW2124P and Merlin series	
Cwatch	Change Cwatch 'Interface does exist' message to <code>NOTICE</code> severity	7078
DHCP	Fix corrupted IA address when sending <code>OPTION_IA_N</code>	7424
Event System	Correctly handle double quotes in event target <code>cmd_template</code> value	5736
	Fix <code>va_event</code> syslog messages showing with no space between date and serial number	7513
GRE	Validate configured keys are unique	6769
HTTP Client	Include all CPUs in interrupt count value in <code>hdl</code> request field <code>irq_cnt</code>	6228
IECD	Added timestamp to <code>iecd show stats</code> diagnostics command	7339
	Enhancement to <code>iecd show config</code> command to show full config and not just main section	6894

	Fix clock sync time in IEC101 <code>force_clock_sync</code> to use local time instead of UTC	7208
	Fix error in converting clock value from IEC104 to UTS seconds	7022
	Fix excessive logging of DNP3 point updates	7521
	Fix serial interface name selectors for DNP3, Modbus and IEC101 to match physical port names	7180
	IEC104 to IEC101 health point now correctly sent to IEC104 master when IEC101 data link gets established	
	Improvements to IEC104 Setpoint to DNP3 Analog Output conversion	7015
IECD/ Modbus	Added bitmap handling for DI register type in Modbus master	7371
	Extend supported data format values for MODBUS data points	6890
	Fix event generation of unsolicited messages for Modbus master (serial) to DNP3 slave (TCP) when DNP3 Unsolicited Messages option is enabled in configuration	7335 7526
	Fix issue with detection of serial interface names on Merlin4400 causing inconsistency with <code>iecd.port.modbus_serial_ifnum</code> option	7051
	Fix issue with IEC104 to Modbus AI scaling	7375
	Fix missing display of point value in Web UI for Modbus to MQTT	7189
	Fix support for conversion of Modbus slave to DNP3 master	7186
	Fixed MODBUS master command not timing out when RTU does not reply	
	Improvements to Modbus trace feature	7470
	Minimum Modbus master polling time reduced from 500ms to 50ms	7228
IECD/DNP3	Added support for DNP3 analog output command g41 v1, v2, v3 and v4	
	Allow non-contiguous point indexes for DNP3 slave	7275
	Changed DNP3 master integrity poll request for class 0 static data poll	7392
	Fix converting DNP3 double precision float types to IEC104 floats	7533
	Fix DNP3 slave to IEC104 master protocol conversion	7579
	Fix incorrect float translation for group 40 var 3 and 4	7536
	Fix issue with converting DNP3 counter to IEC104 Integrated Total	7531
	Fix issue with DNP3 master in processing multi-fragment responses	7409
	Fix to provide output control feedback for DNP3 slave to MODBUS master	
	Fix transmission of spontaneous update to IEC104 master on DNP3 static variation value change	7410
	Fixed issues in DNP3 slave processing Binary Output and Analog Output commands	7548
	Implemented common DNP3 trace functions for slave and master side	7557
	Implemented several new features for IEC104 to DNP3 double command conversion	7423
	Improve DNP3 slave processing of Binary and Analog Commands; now allow all combinations of OpCode and TCC fields: LATCH_ON, LATCH_OFF, CLOSE, TRIP	

	Increased size of DNP3 analog output block buffer to handle possible size of variation 4 – 64 bit double with single byte status	
IECD/MQTT	Fix data point map value update with Modbus master to MQTT conversion that generates events to MQTT subscribers	7465
	Increased supported character length for MQTT topic name, client id and client name	7173
IECD/VHMI	Fix issue related to DPS not starting for VHMI MQTT mode	7081
	Fix to report data point by VHMI only when value changes	
Mobile	Allow backslash '\ ' in username and password	7360
	Custom interface DNS now supported by Unitac modules	7192
	Ensure PDP context is deactivated before attempting to establish connection to avoid issue with connection attempt	7168
	Ensure SMS format is set correctly on the Quectel modules	
	Ensure that we don't try to restore IMS APN settings when using Sierra Wireless WP7702 module	7382
	Fix EID detection when APDU contains the tag and length	7522
	Fix initialisation of 3V/5V SIMs in SIM slot 2 on Merlin 4100/4400 series	7554
		7625
	Fix LTE band selection for bands larger than 63 for Sierra Wireless modules	7680
	Fix mobile module detection on Merlin4100 series	7683
	Fix Quectel registration status poller	7484
	Fix Quectel RM520N restart after switching to QMI mode	7243
	Fix selection of bands above band 63 for SIMCom7600G-H	7356
	Fix SIM In status for Merlin series with non-Sierra Wireless modems	7220
	Fix SIM7070E connection to LTE on Merlin4400 series	7542
	Fix <code>va_mobile</code> failing to start if LTE band list is empty	7495
	Fixed network status constantly changing textual description (LTE/LTE-M) for used radio technology	7340
	Ignore SIM in/out events from eSIM that could lead to crash on Sierra Wireless modems	
	Improve behaviour on network down for QMI connections to ensure reconnection after network outage	6325
	LTE band locking configuration option <code>simX_lte_bands</code> now supports space separated bands	
	<code>sendsms</code> command now handles '+' at the beginning of international numbers	
	Support firmware auto select on Sierra Wireless WP7702	7349
	Unitac modules now use wwan0 interface rather than eth0	6899
Network	Add interface name and state for aliases to <code>network_status</code>	6716
	Fix dependant interfaces starting correctly on a network restart	7598
	Remove the minimum IPv6 fragment size check	7320
		7324
		7325
		7326

OpenVPN	Allow <code>tun</code> or <code>tap</code> setting to create interfaces correctly.	7114
PoE	Fix missing event on powered device disconnect	7195
SCEP	Fix certificate expiration date calculation	7572
	SCEP ATQ time now synchronised with NTP	7083
Serial Broadcast Server	Fixed incorrect handling of TCP connection to Terminal Server	7231
SNMP	Fix UCI MIB <code>ifName</code> truncation	6981
	SNMP <code>engineID</code> now has fixed value that persists through reboot	7355
		7358
Strongswan	General improvements to memory usage	
Syslog	Fix syslog to use local time instead of UTC	7240
System	Adds the ability to define a <code>COMMENT</code> environment variable when invoking any process for display by <code>ps</code> command	7020
	Fix firmware upgrade on Merlin series running Sierra Wireless WP7602 module	7012
	Panic log now contains timestamp on crash events	5608
TACACS	Fix IPv6 support	6620
Terminal Server	Start serial device in RS232 mode to ensure terminal server initialises correctly	7009
VA Event System	Fix buffer overflow crash and add new internal warning event upon event buffer overflow	7176
		7163
VRRP	Allow multiple groups in <code>vrrp status</code> command	7246
Web	Fix reboot via web UI	7574
Web/ Interfaces	Ensure interface names are not automatically capitalized on the web UI	7678
	Remove PPTP protocol from available interface protocols	7354
Web/ Modbus	Fix display of IECD status page to show data points	7170
Web/ Multiwan	Support <code>multiwan.interface.state_transition_hook</code> configuration via the web UI	5433
Web/ OpenVPN	Implement dependency between <code>local</code> and <code>nobind</code> option to avoid OpenVPN failing to start when both enabled in config	6819
Web/ WeConnect	Added support for DCU VPN Concentrator configuration options	
Web/802.1x	802.1x web UI enhancements; add file upload for certs and keys; Only display bridge interfaces as available 802.1x supplicant interfaces	6528
Web/Dynamic DNS	Restart DDNS when settings are changed from web UI	6491
Web/Firewall	Fix add and edit of firewall zones and rules via web UI	7573
	Support firewall rule <code>chain</code> option	6898
	<code>web: security->firewall->traffic rules</code>	
	<code>cli: firewall.rule.chain</code>	
Web/IECD	Change MODBUS serial interface presentation to a selection of detected serial interface names	

	Changed IEC104 TI option to list value instead of range	
	Fix delete button on web UI for IECD	7181
	Fix incorrect display of values in DNP3 slave to DNP3 master mode	7571
	Fixed web UI error in setting value range for IEC104 link number	6911
	IEC61850 client web UI enhancements	6600
	Improvements for IECD command points	7015 7019
	Improvements to MODBUS master configuration	
	Improvements to VHMI web configuration	7062
Web/IOSERV	Add support for upload of CID file	6897
Web/Mobile	Added display of LTE bands supported by SIMCom7070E	7565
	Fix <code>va_mobile</code> restart on save & apply via web UI	7494
	Simplify mobile configuration using tabs via web UI	7707
Web/Mobile Manager	Show supported LTE bands for enable/disable via Web. <code>web: services->mobile manager->lte</code>	
Web/Status	Only show hardware capable features	6966
	Only show multiwan status when enabled	6966
Web/System	Fix duplicate firewall package in configuration export	6904
Web/System	Support missing configuration options for SSH connection identity, verbose and VRF via web UI <code>web: security->ssh->Identity</code> <code>cli: dropbear.dropbear.Identity</code> <code>web: security->ssh->Verbose</code> <code>cli: dropbear.dropbear.verbose</code> <code>web: security->ssh->VRF</code> <code>cli: dropbear.dropbear.VRF</code>	6703
Web/VHMI	Fix broken upload of DPS private key file	
WeConnect	Fix auto generated RIP configuration to ensure WeConnect correctly connects in a Ethernet bridge scenario and also reestablishes on disconnect.	7427 7539 7591
	Fix duplicate interface creation on connect	7547
	Fix support for WeConnect	6793 7218
	HTTPS support for DCU VPN Concentrator auto enrolment	6961

11.6Release 25.03.43.014

Module	Short Description	Mantis
Mobile	Use Unitac-specific AT commands <code>AT!UBAND</code> , <code>AT!UTEMP</code> and <code>AT!UREBOOT</code> instead of GCT commands	
	Added a module reboot after executing a factory reset of the Unitac module	
	Ensure Unitac module comes back in ECM/VLAN mode after factory reset	

	Added an extra delay before issuing the AT command to switch the Unitac modules into ECM mode.	
Web/Realtime Graphs	Fix web UI real time graphs for QMI mobile connections web: status->Realtime Graphs	7029

11.7Release 25.03.43.009

Module	Short Description	Mantis
Activator	Set model URL parameter to uimodel rather than machtype in updates to Activator	6761
Certificates	Improve error reporting for common issues with HTTPS certificates	6987
CLI	Improve error message for <code>uci show xy</code> when <code>xy</code> does not exist	
Ethernet	Add <code>arp-scan</code> utility to DRS, ORK and SXL families for consistency with EDG family cli: <code>arp-scan -l</code>	5829
Firewall	Fix variable name clash in zone option presence test causing occasional restart issue Simplify firewall forwarding within a bridge by avoiding calls to iptables	
Firmware	Prevent downgrade of router firmware to a version that is incompatible with the on board Sierra Wireless module	6878
IECD	Fixed issue with IEC104 clock synchronization on conversion from CP56TIME2A to time format where memory was not being cleared correctly Improvements for Analog Input integer to float conversion for IEC104 to DNP3	
Mobile	Ensure ARP is not turned off for the Unitac Ethernet interface causes problems with the firmware upgrade tool. Ensure NOARP flag is set on mobile Ethernet devices to avoid the ARP table from filling up with entries from the mobile connection Ensure the SMS format is set correctly and interfaces restarted after Verizon provisioning. Fix to ensure the Verizon attach APN is set correctly Only restart interfaces when Network Initialisation was indicated in OMADM Record Unitac AUX antenna values regardless of MIMO state Switch to AT!GSTATUS to retrieve signal information for Unitac modules	6676
OpenVPN	Fix privileges in OpenVPN to allow automatic restarts and fix open SSL errors in WeConnect	6793
SNMP	Correct vaUciMib implementation so that it matches the previous implementation	6903
SNMP/GPS	Fix GPS heading in MIB from degrees to micro degrees	6901
System	Fix issues when config files have execute permissions set and configuration audit is enabled	
TPM	Don't allow loading a new key if a key with the same label is already present	

VLAN	Fix VLAN bridging on Merlin and GW6650V models	6768 6844
Web	Fix error message typo when SSL subsystem fails to initialise Print openssl errors when init, cert load or key load fail	
Web/ Interfaces	Avoid restarting all interfaces when adding new interface via web UI	6922 6923
Web/Cwatch	Fix display of bridge interface on Cwatch interface list	6824
Web/Event System	Support configuration of Event System Digital Input change event input number and value via web UI web: services->va event system->event filters->Input Number cli: va_eventd.forwarding.input_number web: services->va event system->event filters->Input Value cli: va_eventd.forwarding.value	6839
Web/IECD	Added selector lists in place of fixed values where possible	
Web/OSPF	Support configuration of OSPF VRF via web UI web: network->ospf->global settings->VRF cli: ospfd.routing.vrf	6964
Web/PoE	Modifications to a PoE port configuration via the web UI no longer result in the other PoE ports being reset	6827
Web/System	Restore javascript validation preventing underscores in system hostname	4555

11.8Release 25.03.43.000

Module	Short Description	Mantis
BGP	Fix local VRF IP subnet not being advertised over WAN VRF using a BGP instance in the same VRF	6799
Cwatch	Fix cwatch using cached interface values rather than current values which caused cwatch to intermittently miss state changes	6784
IECD	Fix IEC104 operation when IEC104 local TCP port configured to '0'	6778
	Fix unwanted Health Point updates during normal master switchover for IEC104 RTU's	6463
	Fixed Modbus master initialisation error when loading TCP routes	6803
	IEC61850 Server: Add conversion from Modbus DI to DPS objects	
	IEC61850 Server: Added mapping of Modbus DI to integer types (INS, etc)	
	IEC61850 Server: Fix error with double init of data points for Modbus master	
Mobile	IEC61850 Server: Update points from Modbus RTU when point have not been changed before in addition to when value changed	
	Improve debugging of IEC61850 client when processing control commands	
Mobile	Fix signal strength detection on older Unitac modules	6805
	Rename 'phone number' to 'MSISDN' in mobile stats	
SNMP	Fix SNMP configuration using TCP protocol	5930

VRF	Fix DNAT behaviour for alias interface within VRF	6705
Web	Fix slow web SSL access when using keys from TPM	6734
Web/ IPsec	Fix error on saving of configuration general section	6281
Web/ Network	Show colour codes for interface status in network overview	6536
Web/ OpenVPN	Automatically add and remove OpenVPN network interfaces	6296
Web/Firewall	Fix summary page showing rules with <code>option enabled '1'</code> in configuration file as disabled	6765
Web/HTTP Server	Support configuration certificate keys in TPM web: services->http server->Certificate Key Format cli: uhttpd.uhttpd.keytype [PEM TPM]	6756
Web/Mobile	Correct display of mobile interface type on web UI interface overview page	6787
Web/SCADA	Moved COSEM HDLC Bridge configuration from Services to SCADA tab	6781
Web/Status	Add download button for kernel and system log web: status->System Log web: status->Kernel Log	6794

11.9Release 25.02.23.000

Module	Short Description	Mantis
Activator	Fix Activator active update command returning incorrectly parsed IPv6 addresses	4727
CWATCH	Cwatch now ignores non-existing UCI network interfaces	6644
Failsafe	Failsafe mode now uses SSH instead of telnet access	6663
Firewall	Insert the <code>MARK</code> configuration rule before the <code>redirect</code> rules in the firewall table	5405
IECD	Added RTS-CTS flow control of the serial (when not using tserverd)	6615
	Fix issue in IEC104S to IEC101 in transparent mode, where 104 ASDU CA=65535	
	Fix issue processing IEC101 reset process response	
	Fix issue with DNP3 Gr3 (double bit) to IEC104 single point conversion	6671
	Fixed incorrect cleanup while closing during IEC104S TLS session establishment	6636
	Fixed issues with events not sent from IEC104 slave offline queue after connection is restored	6648
	Fixed issues with processing TI 105 Reset Process command	6640
	IEC104 slave: Fixed incorrect application of clock synchronization command	
	IEC104 to IEC101 conversion: fixed issue with converting QU field of commands from Master (104) to RTU (101)	
	IEC104 to IEC104 conversion: Fix Double command Execute part of Select Execute sequence not passing on QU field of command	6656
Mobile	Add MTU detection for Unitac modules	

	Ensure MTU does not exceed 1500 bytes on QMI links	6567
	Ensure Quectel EC25/EG25 modules use GSM format for SMS messages	
	Fix crash when <code>switch_sim</code> command is executed with no value	
	Fix interface name and type for Unitac modules on Merlin series	
	Fix interface name and type for Unitac modules on Merlin series	
	Fix missing LTE band information on older Unitac firmware	6630
	Fix performance issues on Sierra Wireless modules (introduced in 25.02.80.000)	6708
	Prevent <code>+CGEV: NW DETACH</code> trigger warnings in the logs	6616
	Prevent crash when handling SIMs with invalid ICCID	6635
	Prevent crash when no SIM slot specified for SIM switch command	
	va-mobile no longer automatically changes GNSS configuration as this is now done in manufacturing	6659
Monitor	Fix Monitor Keepalive configuration changes taking effect immediately when changed from web UI or Activator	6650
NTP	Improvements to chrony operation for interface state changes	6631
PPP	Fix connection issue when two ppp links have similar UCI name	6654
Roaming Manager	Retry existing connection after routine disconnect when using Roaming Manager feature	
Routing	Enable FRR <code>vtty_enabled</code> option in user interface	6613
SFP	Support <code>ethtool -m</code> option for displaying SFP info	
SNMP	Fix mibwalk error on <code>.1.3.6.1.4.1.2078.3.1.2.4.2</code> when walking VA-MODEM-MIB:: <code>roamingOp*</code> series of values	6618
SSH	Fix SSH login via private and public key.	6425
TACACS	Fix ipv6 address support	6620
Web	Sort web UI drop down headings	5909
Web/ Multiwan	Allow multiwan configuration via web UI when no multiwan config options exist in configuration file	
Web/BGP	Fix BGP network option for IP address/subnet input rather than interface name web: network->bgp->global settings->Network	6619
	Fix BGP network option for IP address/subnet input rather than interface name web: network->bgp->global settings->Network	6619
Web/HTTP Client	Support configuration of Http Client certificate key format web: services->http client->advanced->Certificate Key Format cli: httpclient->httpclient->KeyFormat	5792
Web/IECD	Changed default location of TLS certs to <code>/etc/cert</code>	6643
	Only show <code>IEC104 TLS Common Name</code> and <code>IEC104 TLS Verify Depth</code> options when <code>IEC104 TLS Validate Peer Cert</code> is enabled	6643
	Removed unused <code>iec101_cmd_type_id</code> option from web UI	6627
	Support SCL import file upload for IEC61850 master web: scada->iecd->master protocols->configure IEC61850->Select IEC61850M SCL File for Upload	

	Support upload capability for TLS cert, key and CRL files via web UI	6643
Web/IPsec	Web UI IPSEC configuration improvements	6281
Web/System	Fix firmware flashing error message	6286
Web/VRRP	Add support for configuration of VRRP Group Multicast Source IP web: network->vrrp->vrrp group configuration-> Multicast Source IP cli: vrrp.vrrp_group.mcast_src_ip	4057

11.10 Release 25.02.99.000

Module	Short Description	Mantis
CWATCH	Ensure cwatch can handle comma separated ping destinations	
GRE	Fix GRE keepalives	6554
IECD	Added conversion from 4 Modbus 16-bit registers (int64) to iec104 float	
	Added support for conversion of 2 modbus 16-bit registers storing FLOAT32 to IEC104 type 13 float	
	Fetch CRL file using a link from peer certificate	5955
	Fix CSV import issue when parsing bitmap options	6555
	Fix issue in IEC61850 master to DNP3 slave conversion of analog float values	6593
	Fix serial configuration in modbus master	6540
	Fix tx buffer overflow and iecd crash when DNP3 Slave serving large number of points and events (500+)	6609
	Handle multiple sessions, cleaning up in case of errors when fetching CRL file using a link from peer certificate	5955
	Improved IEC61850 control command processing in relation to IEC101 and IEC104 single-double select-execute sequence	
	Improved IEC61850 SCL import and export into UCI file	6581
	Improved show statistics command when multiple RTU protocols are used per point	6580
	Improvements in the VRTU to IEC61850 slave conversion	
	MQTT Slave to MODBUS RTU: send MQTT publish only on value change	6376
	Support configurable IED name and LD name for IEC61850 slave web: scada->iecd->slave protocols->configure iec61850->IEC61850 IED Name cli: iecd.port.iec61850_ied_name web: scada->iecd->slave protocols->configure iec61850->IEC61850 LD Name cli: iecd.port.iec61850_ld_name	
	Support for Digital Input inversion in the IEC61850 server	
Mobile	Add data-only configuration for Quectel EP06 module	
	Add display of additional Unitac signal values to vam command and web UI	
	Disable the APNs when connection is terminated for Unitac modules	6484
	Fix for SMS received by Quectel EG25G via IMS in Verizon network	6594

	Mobile connection no longer dropped when 2 nd antenna is disconnected when using Unitac modules	6446
	Support new option to enable MIMO on Unitac modules (disabled by default). web: services->mobile manager->advanced->Enable MIMO for Unitac radio Modules cli: mobile.mobile.unitac_mimo_enabled	6499
Network	Fix dependent interface behaviour when parent WAN interface is using QMI mobile interface	6493
QoS	Fix QoS initialisation	6560
SCEP	Fix intermittent issue where only one SCEP request was sent when multiple SCEP clients were configured	6523
	Fix loading of SCEP CA certificate	6525
Strongswan	Do not split long PSK into separate lines which would cause PSK to be read incorrectly and Phase1 failure	6537
Syslog	Fix multiwan errors in log when multiwan not configured	6489
System	Prevent download of incorrect firmware family	
TACACS	Fix tab correction for TACACS+ user login via SSH	6527
Terminal Server	Fix failure to recover from bind failure while interface down	6464
TPM	Fix RSA key loading on big endian platforms	
	Improve support for TPM access from multiple processes to avoid TPM being locked by another process	6483
User Limits	Fix Procrustes user limit events	6538
Web	Fix web UI intermittently advising router is running in factconf when in config1	6547
Web/ Interfaces	Fix default gateway handling for DHCP protocol	6601
Web/IECD	Fix typo in DNP3 slave protocol option	6578
	Fix web UI issue in IEC61850 slave	
Web/Mobile	Prevent option <code>ifname</code> configuration being added to mobile interfaces when configured via web UI	6501
Web/SNMP	Improvements to web UI SNMP configuration	
WiFi	Fix <code>ifup</code> transmission issue when WiFi is bridged with an Ethernet interface	6514

11.11 Release 25.02.80.000

Module	Short Description	Mantis
Ethernet	<code>ifup</code> now preserves VLAN interfaces when configuration has non VLAN and multiple VLANs attached to the same Ethernet interface	6247
	Increase frame size limit to accommodate large VLAN packets	6307
Event System	Fix boot success event	5927
GPIO	Merlin4600 digital inputs now default to dry	5992

IECD	Added missing implementation of T0, T1 and T3 timers to address IEC104M link not closing on ifdown	
	<pre>web: scada->iecd->master protocols->configure iec104->iec104-X cli: iecd.port.iec104m_t0 (def: 5 secs) cli: iecd.port.iec104m_t1 (def: 15 secs) cli: iecd.port.iec104m_t3 (def: 20 secs)</pre>	
	Fix parsing parsing of -casdu switch in IEC104 firewall	6298
	Fixed incorrect parsing of MQTT SUB-ACK packet	6295
	Fixed load errors for custom SCADA firewall rules	6025
	Fixed MQTT hostname resolution	6308
Mobile	Add switch to add switch to data-centric mode for Quectel EC25 and SIMCOM modules	
	Added PCI display for Unitac modules	6251
	Ensure that Verizon APN is correct for default/initial bearer	6154
	Enter airplane mode before attempting to change the default LTE bearer to avoid issues with SIM failover	5991
	fix chat command failing if previous chat aborted	6210
	Fix crash when LTE band retrieval for SIMCOM fails	
	Fix ESN display where leading zeros were being omitted	6345
	Fix incorrect reporting of RSSI when using Unitac mobile module	6437
	Fix multiwan to run with default group when no group name specified	
	Fix to prevent the modification of the Verizon attach bearer	6043
	Fix va_roaming ignoring stat=0 operators in roaming scan	6184
	Ignore network provided DNS addresses if option DNS configured	6372
	Improvements to operator scan:	
	<ul style="list-style-type: none"> Now commence an operator scan as follows; AT+COPS=2 (detach from network); AT+COPS=0;+COPS=? (reattach and commence scan, all in one operation) AT+COPS=? timeout increased to 190 seconds automatically retry a failed AT+COPS=? command if it fails within 15 seconds vam roaming now includes scan duration in seconds 	
	Incorrect SINR reported for Quectel modules	5951
Re-connect to network automatically if AT+CGATT=1 fails		
VA Mobile roaming diagnostic now shows roaming info for all modems by default		
cli: vam roaming		
Network	Ensure ifdown kills all ifup processes on the same interface and not just the child processes	
	Fix repeated ifup race condition on bridged interfaces	6265
RTUD	Added support for inverting digital inputs after reading from hardware	6208
<pre>web: scada->rtud->advanced->Invert Inputs cli: rtud.main.invert_inputs (def: 0)</pre>		
SCEP	Added certificate expiry check during re-enrolment	6235

	Change new cert and key permissions when they are installed at the end of the SCEP process. Also adjust the CRLs directory to allow strongswan write access for runtime CRL downloads.	5908
	Strongswan is now restarted after SCEP renewal to ensure the peer correctly deletes the existing IKE_SA	6190
SFP	Merlin4600 now supports both 100M and 1000Mbps using SIGMII mode	
SNMP	Fix creation of SNMPv3 traps	5943
	Fix failing snmpwalk on vaModem MIB when no roaming info available	5922
Strongswan	Allow IPsec tunnels to start when CA certificate download fails and blocking is disabled in <code>scep_cert</code> config	6324
	Remove FlexVPN GRE IP addresses on tunnel termination	5924
	Fix IKE SA delete being sent with correct message id to ensure IPsec peer does not discard	6246
System	Changed password hash algorithm option value to a ListValue <code>cli: list system.main.passwrld_hash_algo</code>	5001
	Fix auditing of DMVPN configuration using option <code>audit_cfg</code>	
	Fix boot-success script to set altimage to current image to avoid Merlin4400/4600 series incorrectly reverting to altimage	6392
Terminal Server	Increase port limit to 16	6267
	Added support for new option in GW2124P to control serial LED detection using DSR control signal when DTR/DSR signals are being used <code>cli: tserverd.port.led_dsr_detect (def: 0)</code>	
	Auto detect serial mode gpio control settings	5970
	Fix SNMP poll of TSERVER-MIB	6477
	Fixed issue with auto detection of serial port names on GW2028	6313
Web	Improvements to web UI performance and load times	6178
Web/ Ethernet	Fix Ethernet adapter interfaces presented in web UI for Merlin4600 series	5986
	Remove Ethernet Port map section in web UI for Merlin4400/4600 series. Mapping configured in Etherent interface view.	5986
Web/ Interface	Added <code>mtu</code> configuration option for PPPoEoA and PPPoA ADSL interfaces	5702
Web/ OpenVPN	Do not add <code>key_direction</code> option when set to its default value (bidirectional) when OpenVPN configured via web UI	6063
Web/GPIO	Change Web UI digital input mode default to dry mode	6060
Web/IECD	Changed free text fields <code>log_vaevent_on_change</code> , <code>vhmi_on</code> and <code>vhmi_dword</code> to selector on-off	6165
Web/Terminal Server	Added support for TCP Tap Port configuration <code>web: scada->terminal server->port->advanced->TCP Tap Port</code> <code>cli: tserverd.port.tap_port (def: 0)</code>	6291
Web/VA Event	Add length check in web UI for <code>snmp_auth_pass</code> and <code>snmp_priv_pass</code>	
Web/WiFi	Add WPA Enterprise configuration to web	5963

11.12 Release 25.02.14.032

Module	Short Description	Mantis
Download	Fix interrupted download when va_vars incorrectly states image not found. Download now correctly continues rather than starting again.	6354
Mobile	Fix duplicated ICCID when using WP76xx-AU module on Merlin4600 series.	6352
TACACS	Fix TACACS behaviour when router is configured to only authorise authentication for SSH access (or other configured PAM services). Previously all authentication requests were sent to TACACS server instead of SSH only.	6050
TPM	Fix HTTPS incoming connection activation with key stored in TPM on Merlin4600 series. Flush transient objects from TPM RAM upon session open on Merlin4600 series.	6367

11.13 Release 25.02.14.027

Module	Short Description	Mantis
BFD	BFD rate changes now working as expected when multihop enabled	6255
	Fix BFD multiplier configuration	6242
Download	Fix size calculation when image download exceeds 10M	6033
	Increase time limit for image download to 5 hours (previously 2 hours)	6266
HTTP Client	Set download minimum rate limit to 1kBps	6266
PPPoE	ifup <ifname> now correctly re-establishes when <ifname> is a PPPoE link and is already up	6241
Terminal Server	Fix incorrect translation of <code>option serialPortName</code> Fix TOS value support using <code>option tos_value</code>	

11.14 Release 25.02.14.016

Module	Short Description	Mantis
GPIO	Merlin4600 series digital input values changed to match GW2020 series for SCADA operation compatibility 0 = input not detected/open/low 1 = input detected/closed/high	6197

11.15 Release 25.02.14.013

Module	Short Description	Mantis
Ethernet	Fix default MAC address for Merlin4600 Ethernet ports	5740
GPIO	Merlin series digital inputs now default to dry	5992
IECD	Fix data point handling where previously only the last data point was forwarded the SCADA master when using HART protocol	6046

	Fix IECD CSV files data point import.	5975
	Fix issue in handling periodic GI and Clock Sync timeouts in IEC101 Master	
	Support for CP24 timestamp format messages in IEC101 to 104 conversion	5980
Mobile	Fix crash when LTE band retrieval for SIMCom fails	
SFP	Fix interface failing to restart after network package restart	6079
Strongswan	Decrease OCSP/CRL fetch timeout to 3 seconds from 10 seconds to avoid resource issues for multiple tunnels using CRL	5954
	Exclude password field from re-enrollment requests	5993
	Handle DER or PEM format for SECP fingerprint	5879
	In case multiple root CA's downloaded, verify fingerprint of the root	
	Send DELETE message from IKEv2 delete task for initiator. Previously when initiator, the router terminated the IKE_SA without sending a delete which led to problems when connected against another VA router in responder role.	6052
System	Backup, check and fix uboot environment in case of corruption on models using Sierra Wireless WP7600 series processor (GW1150, Merlin4600). Fixes rare situation where machtype could revert to incorrect model.	6031
Terminal Server	Fix loopback test for serial ports	5972
Web/IPsec	Support configuration for FlexVPN via web UI web: services->ipsec->connection->Route Interface cli: strongswan.connection.route_interface web: services->ipsec->connection->FlexVPN Prefixes cli: strongswan.connection.flexvpn_prefixes	6000
	Support configuration of local cert via web UI web: services->ipsec->scep certificate->Local Certificate cli: strongswan.connection.localcert	6000
Web/RTUD	Fix defaults for Web UI fields to allow web config to save the page	6075
	RTUD auto generate config option now defaults to off in both web UI and router web: scada->rtud->main settings->Auto generate configuration cli: rtud.rtud.point_auto_config_on	6075
Web/SCEP	Support configuration of SCEP fingerprint and CA Name via wb UI web: services->ipsec->scep certificate->CA Fingerprint cli: strongswan.scep_cert->fingerprint web: services->ipsec->scep certificate->CA Name cli: strongswan.scep_cert->ca_name	6001
Web/Terminal Server	Support configuration of serial port name via the web UI web: scada->terminal server cli: tserverd.port.serialPortName	5424

11.16 Release 25.02.14.002

Module	Short Description	Mantis
IECD	Fix IEC MIB walk	5920
IOSRVD	Fix for option auto_detect behaviour to not remove undetected devices from iosrvd config file	5522
Mobile	Fix ICCID collection for second SIM on Sierra Wireless and Quectel EM06 modules. Previously showing same ICCID for both SIMs	5946
Network	Fix static default route configuration using target 'default' and netmask 0.0.0.0	5942